

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

AVR Series 230V 750VA 450W Ultra-Compact Line-Interactive UPS with USB port, C13 Outlets

MODEL NUMBER: AVRX750U











Description

Tripp Lite's AVRX750U Ultra-Compact Line Interactive UPS offers complete power protection for desktop PCs, network workstations and a wide variety of professional and consumer electronic devices.

Uninterruptible Power Supply / UPS circuits switch to battery backup mode within milliseconds to keep connected equipment running without interruption or data loss during power failures. Automatic Voltage Regulation / AVR power conditioning maintains smooth, continuous operation of connected equipment during brownouts and overvoltages. Surge-only outlets offer convenient protection for printers and other desktop accessories not requiring battery support. AC and dataline surge suppression prevents connected equipment damage. USB communications port supports built-in power management and auto-shutdown features of Windows and Mac OS X or full featured monitoring and data-saving auto-shutdown options using Tripp Lite's free PowerAlert monitoring software.

Features

- AVRX750U ultra-compact 230V line interactive UPS offers complete AC power protection from blackouts, brownouts and transient surges
- 750VA / 450 watt UPS output capacity
- Uninterruptible Power Supply / UPS operation maintains battery-derived AC output during blackouts to prevent data loss and system downtime for connected equipment
- Built-in USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- HID-compliant USB port also enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Automatic Voltage Regulation / AVR corrects extended brownouts and overvoltages from 159 to 282V,
 without using battery power
- 2.4 minutes runtime at 100% load (450 watts), 8.6 minutes runtime at 50% load (225 watts)

Highlights

- 750VA ultra-compact 230V line interactive UPS
- Corrects brownouts and overvoltages from 159V to 282V
- 3 UPS battery supported outlets,
 3 surge-only outlets
- USB port, TEL/DSL protection, Wall mountable
- C14 inlet and 6 C13 outlets

Package Includes

- AVRX750U UPS System
- USB cable
- Two C13 to C14 power cables
- Instruction manual



- 32 minutes runtime for a desktop computer system consuming 80 watts continuous
- 6 total C13 outlets; Includes two 2m C13 to C14 power cables
- 3 UPS battery backup outlets, plus 3 additional surge-only outlets
- C14 inlet supports a variety of site specific input cordsets
- Network grade AC surge and lightning protection is available from all outlets; Built-in data line surge suppression protects a single dialup or DSL line
- Supports Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application/OS or hard power off/on reboot of connected equipment, ideal for unattended kiosk applications
- Built-in grounding lug
- Hot swappable user battery replacement
- Optional PDUBHV10 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment
- · Space saving, ultra-compact housing with support for wall-mount, desktop or floor placement

Specifications

OVERVIEW		
UPC Code	037332123138	
UPS Type	Line-Interactive	
INPUT		
Rated input current (Maximum Load)	10A	
Nominal Input Voltage(s) Supported	230V AC	
UPS Input Connection Type	C14 inlet	
UPS Input Connection Description	Attached 15cm line cord with C14 inlet. The C14 inlet accepts user-supplied AC power cord with country specific plug.	
UPS Input Cord Length (ft.)	0.5	
UPS Input Cord Length (m)	0.2	
Input Phase	Single-Phase	
ОИТРИТ		
Output Volt Amp Capacity (VA)	750	
Output Watt Capacity (Watts)	450	
Nominal Voltage Details	230V nominal output in battery mode	
Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	Automatic frequency selection	





Output Voltage Regulation (Line Mode) Included Output Power Cables Includes 2 C13 to C14 output power cables UPS Output Receptacles (Surge Suppression Office) Included Output Power Cables Includes 2 C13 to C14 output power cables UPS Output Receptacles (Surge Suppression Office) Included Output Power Cables Includes 2 C13 to C14 output power cables UPS Output Receptacles (Surge Suppression Office) Included Output AC Waveform (AC Mode) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) Voltage (S) Supported Upt C Upt (S) Supported			
Included Output Power Cables Includes 2 C13 to C14 output power cables UPS Output Receptacles (Surge Suppression Only) 3 UPS outlets, 3 surge-only outlets 3 UPS outlets, 3 surge-only outlets Hot-Swap PDU options PDUBHV10 (2U / 8 C13 outlets) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery PWM sine wave Nominal Output Voltage(s) 220V; 230V; 240V Output AC Waveform (Battery PWM sine wave Nominal Output Voltage(s) 220V; 230V; 240V Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Full Load Runtime (min.) 2.4 min. (450w) 4 min. (450w) 4 min. (450w) 4 min. (450w) 12 12 12 12 13 13 13 13	Output Voltage Regulation (Line Mode)	+8%, -21%	
UPS Output Receptacles (Surge Suppression Only) Hot-Swap PDU options PDUBHY10 (2U / 8 C13 outlets) Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) Supported Output AC Waveform (Battery Mode) Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) Supported Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 8.6 min. (225w) DC System Voltage (VDC) 12 Internal UPS Replacement Battery Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status		+/- 5%	
Hot-Swap PDU options PDUBHV10 (2U / 8 C13 outlets) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery pWM sine wave Nominal Output Voltage(s) 220V; 230V; 240V Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 8.6 min. (225w) DC System Voltage (VDC) 12 Internal UPS Replacement Battery Cartridge Tripp-Lite-APC-Belkin-Battery Access Battery Access Battery access door Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible alarm indicates power-failure and overload/check battery status LED Indicators 2 LEDs indicate power status and overload/check battery status	Included Output Power Cables	Includes 2 C13 to C14 output power cables	
Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) Supported 220V: 230V: 240V Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 8.6 min. (225w) DC System Voltage (VDC) I2 Internal UPS Replacement Battery Cartridge "Access Battery access door Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and overload/check battery status LED Indicators 2 LEDs indicate power status and overload/check battery status	UPS Output Receptacles (Surge Suppression Only)	3 UPS outlets, 3 surge-only outlets	
Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported 220V; 230V; 240V Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) B.6 min. (225w) DC System Voltage (VDC) Iternal UPS Replacement Battery Cartridge Battery Access Battery Access Battery Access Battery Access Battery Access Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible Alarm Audible alarm indicates power-failure and overload/check battery status LED Indicators 2000; 240V 220V; 230V; 240V 24mV 450w) 460	Hot-Swap PDU options	PDUBHV10 (2U / 8 C13 outlets)	
Nominal Output Voltage(s) Supported 220V; 230V; 240V Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 2.5 min. (225w) DC System Voltage (VDC) Internal UPS Replacement Battery East-Powerware-Liebert-other-UPS-RBC51*>RBC51*/a> Battery Access Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible Alarm Audible alarm indicates power failure and overload/check battery status LED Indicators 2 LEDs indicate power status and overload/check battery status	Output AC Waveform (AC Mode)	Sine wave	
Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 8.6 min. (225w) DC System Voltage (VDC) 12 Internal UPS Replacement Battery Cartridge 8hbspca class="productLink" href="//www.tripplite.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belkin-Best-Powenware-Liebert-other-UPS-RBC51">	Output AC Waveform (Battery Mode)	PWM sine wave	
BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 2.5 min. (25w) DC System Voltage (VDC) Internal UPS Replacement Battery Cartridge Battery Access Battery Access Battery Access Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and overload/check battery status LED Indicators 2.4 min. (450w) 4.4 min. (450w) 8.6 min. (225w) 8.6 min. (225w) 12 Internal UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belkin-Best-Powerware-Liebent-other-UPS-RBCS1'>RBCS1'/a> Battery Access Battery Ac	Nominal Output Voltage(s) Supported	220V; 230V; 240V	
BATTERY Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 8.6 min. (225w) DC System Voltage (VDC) 12 Internal UPS Replacement Battery RBC51">RBC51">RBC51 - Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Output Receptacles	(6) C13	
Full Load Runtime (min.) 2.4 min. (450w) Half Load Runtime (min.) 8.6 min. (225w) DC System Voltage (VDC) 12 Internal UPS Replacement Battery Cartridge Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible Alarm Audible alarm indicates power-failure and overload/check battery status LED Indicators 2. LEDs indicate power status and overload/check battery status	Individually Controllable Load Banks	No	
Half Load Runtime (min.) DC System Voltage (VDC) 12 Internal UPS Replacement Battery	BATTERY		
DC System Voltage (VDC) Internal UPS Replacement Battery Eartridge RBC51">RBC51">RBC51">RBC51">RBC51 > Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Full Load Runtime (min.)	2.4 min. (450w)	
Internal UPS Replacement Battery Cartridge RBC51">RBC51">RBC51">RBC51">RBC51">RBC51 -RBC51">RBC51-RBC51">RBC51-RBC51">RBC51-RBC51">RBC51-RBC51">RBC51-RBC51">RBC51-RBC51-RBC51">RBC51-RBC51-RBC51">RBC51-RBC51-RBC51-RBC51">RBC51-RBC	Half Load Runtime (min.)	8.6 min. (225w)	
Battery Access Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	DC System Voltage (VDC)	12	
Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Internal UPS Replacement Battery Cartridge	RBC51	
Expandable Runtime No VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Battery Access	Battery access door	
VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Battery Replacement Description	Hot-swappable, user replaceable batteries	
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Expandable Runtime	No	
Overvoltage Correction Input voltages between 245 and 282 are reduced by 12% Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	VOLTAGE REGULATION		
Undervoltage Correction Input voltages between 159 and 205 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 159 to 282VAC	
USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Overvoltage Correction	Input voltages between 245 and 282 are reduced by 12%	
Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	Undervoltage Correction	Input voltages between 159 and 205 are boosted by 14%	
Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status	USER INTERFACE, ALERTS & CONTROLS		
LED Indicators 2 LEDs indicate power status and overload/check battery status	Switches	Combination switch controls on/off power status and self-test operation	
	Audible Alarm	Audible alarm indicates power-failure and overload status	
SURGE / NOISE SUPPRESSION	LED Indicators	2 LEDs indicate power status and overload/check battery status	
UPS AC Suppression Joule Rating 320	UPS AC Suppression Joule Rating	320	
UPS AC Suppression Response Time Instantaneous	UPS AC Suppression Response Time	Instantaneous	





UPS Dataline Suppression	1 line TEL/DSL (1 in / 1 out)	
EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Installation Form Factors Supported with Included Accessories	Tower; Ultra-compact desktop; Wallmount	
Primary Form Factor	Desktop	
Primary UPS Depth (mm)	178	
Primary UPS Height (mm)	102	
Primary UPS Width (mm)	305	
Shipping Dimensions (hwd / cm)	13.72 x 24.89 x 36.83	
Shipping Dimensions (hwd / in.)	5.40 x 9.80 x 14.50	
Shipping Weight (kg)	6.75	
Shipping Weight (lbs.)	14.89	
UPS Housing Material	ABS	
UPS Power Module Dimensions (hwd, cm)	10.16 x 30.48 x 17.78	
UPS Power Module Dimensions (hwd, in.)	4 x 12 x 7	
UPS Power Module Weight (kg)	6.49	
UPS Power Module Weight (lbs.)	14.3	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	20	
Battery Mode BTU / Hr. (Full Load)	459	
AC Mode Efficiency Rating (100% Load)	98%	
COMMUNICATIONS		
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at http://www.tripplite.com/poweralert	
Communications Cable	USB interface cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Network UPS Tools Compatibility	NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at http://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite	
Communications Interface	USB (HID enabled)	





LINE / BATTERY TRANSFER		
Transfer Time	2-4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	159	
High Voltage Transfer to Battery Power (Setpoint)	282	
SPECIAL FEATURES		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS	
STANDARDS & COMPLIANCE		
UPS Certifications	CE; Tested to GOST (Russia); Tested to SASO (Saudi Arabia); Meets FCC Part 15 Category B (EMI)	
WARRANTY		
Product Warranty Period (International)	2-year limited warranty	

© 2020 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies