



Quality Products. Service Excellence.

Tube Guitar Amplifier - Output Transformers 1750 Series

REPLACEMENT & UPGRADES



Features

- Designed for drop in replacement of original units.
- Physically, parts were designed to look similar to original factory units (where possible).
- Material used & design specs. were kept as close as possible to the original part to preserve the stock "tone".
- Output transformers marked UPGRADE (below) allow for more versatility by added secondary connections that did not exist on the original units.



Fender (Output Transformers)

Hammond P/N	Fender Amp	Similar Fender P/N's*	Fender Chassis No.s*	Pri Ohms	Sec Ohms	Amplifier Type	Watts	Winding
1750A				22800	8	Single Ended	3.5	Bobbin
1750AB				9000	8	Push-Pull	12	Bobbin
1750AX				7500	8	Single Ended	3.5	Bobbin
1750B				5482	8	Single Ended	10	Paper
1750C	Bronco* Champ*	125A35A, 022905, 125A3A	Blackface*, Silverface*, AA764, AB764 Tweed*, 5C1, 5E1, 5F1, Vibro Blackface*	5,000/8,000	3.2	Single Ended	5	Bobbin
1760C	Bronco* Champ*	125A35A, 022905, 125A3A	Blackface*, Silverface*, AA764, AB764 Tweed*, 5C1, 5E1, 5F1, Vibro Blackface*	5,000/8,000	3.2, 8, 16	Single Ended	5	Bobbin
1750D				2350	4, 8, 16	Push-Pull	100	Paper
1750E	Deluxe 5E3*	50246		8,500 C.T.	8	Push-Pull	15	Paper
1760E	Deluxe 5E3*	50246		8,500 C.T.	4, 8, 16	Push-Pull	15	Paper
1750F	Blues Junior*	49969		6,950 C.T.	8	Push-Pull	15	Paper
1760F	Blues Junior*	49969		6,950 C.T.	4, 8, 16	Push-Pull	15	Paper
1750H	Deluxe* Deluxe 68 Custom Reverb* Deluxe Reverb 65 Reissue*	125A1A, 022640, 041318		6,600 C.T.	8	Push-Pull	20	Paper
1760H	Deluxe* Deluxe 68 Custom Reverb* Deluxe Reverb 65 Reissue*	125A1A, 022640, 041318		6,600 C.T.	4, 8, 16	Push-Pull	20	Paper

Hammond P/N	Fender Amp	Similar Fender P/N's*	Fender Chassis No.s*	Sec Amplifier					
				Pri Ohms	Ohms	Type	Watts	Winding	
1750J	Bandmaster*	125A6A, 022848, 125A7A	Blonde, 6G7-A, Blackface, AA763, Silverface, AC568, AD1269, Blackface Reverb, Reverb, Reverb AA763, Silverface Reverb, Reverb AA1069, Reverb AA270	4,000 C.T.	4	Push-Pull	40	Bobbin	
1760J	Bandmaster*	125A6A, 022848, 125A7A	Blonde, 6G7-A, Blackface, AA763, AB763, Silverface, AC568, AD1269, Blackface Reverb, Reverb, Reverb AA763, Silverface Reverb, Reverb AA1069, Reverb AA270	4,000 C.T.	4, 8, 16	Push-Pull	40	Bobbin	
1750JA	Deluxe Blues*	47269		4,250 C.T.	4, 8	Push-Pull	40	Paper	
1760JB	Bandmaster*	45216, 1846, 1848	Tweed	6,000 C.T.	2.67, 4, 8	Push-Pull	40	Bobbin	
1750K	Bassman*	125A9A, 022855	Tweed	4,000 C.T.	2	Push-Pull	50	Paper	
1760K	Bassman*	125A9A, 022855	Tweed	4,000 C.T.	2, 4, 8	Push-Pull	50	Paper	
1750KA	Bassman 59 Reissue* Concert*	36485, 125A9A, 022855	6G12, 6G12A, AA763, Blackface*, Brownface*	4,150 C.T.	2	Push-Pull	50	Paper	
1750M	Super Concert 93*	41754		4,200 C.T.	2, 4, 8	Push-Pull	60	Bobbin	
1750L	Bassman*	022871, 125A13A	5F6, 5F6A, 10, Blackface, AA864, AA165, AB165, Silverface, AA270	4,200 C.T.	4	Push-Pull	60	Paper	
1760L	Bassman*	022871, 125A13A	5F6, 5F6A, 10, Blackface, AA864, AA165, AB165, Silverface, AA270	4,200 C.T.	4, 8, 16	Push-Pull	60	Paper	
1750W	Bassman 100*	125A29A, 022689, 022889, 022899, 037612		2,000 C.T.	4	Push-Pull	100	Paper	
1760W	Bassman 100*	125A29A, 022689, 022889, 022899, 037612		2,000 C.T.	4, 8, 16	Push-Pull	100	Paper	
1750D				2,350 C.T.	4, 8, 16	Push-Pull	100	Paper	
1750WA	Bassman 100*	125A29A, 022689, 022889, 022899, 037612		2,000 C.T.	2, 4, 8	Push-Pull	100	Bobbin	
1750WR	Bassman 135*	13691		2,000 C.T.	4, 8	Push-Pull	135	Paper	

Marshall (Output Transformers)

Part No.	Pri Ohms	Sec Ohms	Amplifier Type	(Watts)	Bobbin/Paper Winding	Model Names	Similar to (MFG Part No.)
						(There may be more)	(There may be more)
1750FA	7,000 C.T.	8, 16	Push-Pull	15	Bobbin	DSL15H	DSL-15 OPT
1750PA	8,400 C.T.	4, 8, 16	Push-Pull	18	Paper	18 Watt Combo	-
1750NA	6,000 C.T.	8, 16	Push-Pull	30 - 60	Bobbin	JTM30, JTM60	Drake 292-772
1750N	3,200 C.T.	4, 8, 16	Push-Pull	50	Bobbin	JMP, JCM 800	-
1750P	126, 500, 2,000	2, 4, 8, 16	Push-Pull	50	Bobbin	JCM 900	-
1750Q	7,371 C.T.	4, 8, 16	Push-Pull	50	Bobbin	JTM 45	-
1750U	1,700 C.T.	4, 8, 16	Push-Pull	100	Bobbin	JMP, JCM 800	-
1750X	1,700 C.T.	2, 4, 8, 16	Push-Pull	100	Bobbin	JCM 900	-

VOX (Output Transformers)

Part No.	Pri Ohms	Sec Ohms	Amplifier Type	(Watts)	Bobbin/Paper Winding	Model Names	Similar to (MFG Part No.)
						(There may be more)	(There may be more)
1750Y	6,200 C.T.	8	Push-Pull	15	Bobbin	AC15	-
1750V	4,000 C.T.	8, 16	Push-Pull	30	Paper	AC30 Vintage	-
1750T	4,000 C.T.	8, 16	Push-Pull	30	Bobbin	AC30 Reissue	-

Yorkville/Traynor (Output Transformers)

Part No.	Pri Ohms	Sec Ohms	Amplifier Type	(Watts)	Bobbin/Paper Winding	Model Names	Similar to (MFG Part No.)
						(There may be more)	(There may be more)
1750Z	10,000 C.T.	8	Push-Pull	20	Paper	Bass Mate YBA-2	A1313

Part No.	Pri Ohms	Sec Ohms	Amplifier Type	(Watts)	Bobbin/Paper Winding	Model Names (There may be more)	Similar to (MFG Part No.) (There may be more)
1750S	5,100 C.T.	8	Push-Pull	25	Paper	Base Mate YBA-2B	A1339
1750G	3,800 C.T.	4, 8, 16	Push-Pull	50	Paper	Replaces 92105	A1312
1750R	2,000 C.T.	4, 8, 16	Push-Pull	100	Paper	Replaces 98694	A1301
93405 ¹	1900 C.T.	8	Push-Pull	120	Paper	YBA-3	A1332

¹ Part number 93405 is built by special order only. Please contact Hammond's sales team for more information.

Orange (Output Transformers)

Part No.	Pri Ohms	Sec Ohms	Amplifier Type	(Watts)	Bobbin/Paper Winding	Model Names (There may be more)	Similar to (MFG Part No.) (There may be more)
1750ORF	6,000 C.T.	8, 16	Push-Pull	35	Bobbin	Rocker 30	OT119SL

* DISCLAIMER: Hammond Mfg. is not affiliated with Fender Musical Instruments Corp., Marshall Amplification, Yorkville/Traynor, AMPEG or VOX Amplification companies. Amplifier model names are trademarks of the Amplifier companies and are just listed here for reference purpose only.

Data subject to change without notice

© 2020. Hammond Manufacturing Ltd. All rights reserved.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Hammond:

[1750A](#) [1750C](#) [1750E](#) [1750F](#) [1750H](#) [1750J](#) [1750K](#) [1750L](#) [1750M](#) [1750N](#) [1750P](#) [1750T](#) [1750U](#) [1750V](#) [1750W](#)
[1750X](#) [1750G](#) [1750Y](#) [1760C](#) [1760E](#) [1760F](#) [1760H](#) [1760J](#) [1760K](#) [1760L](#) [1760W](#) [1750NA](#) [1750KA](#) [1750Q](#)
[1750R](#) [1750PA](#) [1750S](#) [1750JA](#) [1750D](#) [1750WR](#) [1750AX](#) [1750B](#) [1750Z](#) [1750ORF](#) [1750FA](#) [1760JB](#) [1750WA](#)