

Accessories

L-Series Circuit Breakers



LISTED
E305318

Accessories can be factory or field mounted on L-Series miniature molded case circuit breakers for enhanced control and monitoring capabilities. Field mounting kits include all necessary parts and instructions. Accessories can be gang mounted on a single controller (the Auxiliary Switch in the outside position). The mounting arrangement links the internal latch-pins for the tripping mechanisms, ensuring simultaneous trips. Handles are linked to simplify manual resetting.



Neutral Pole (63A/240VAC; 32A/480Y/277VAC)

Description	Type/ Cat. No.	Cable Max	Cable Min	Torque Max	Torque Min
Neutral	ALTN2L	25mm ² 3 AWG	2.5mm ² 12 AWG	2Nm 17.5 lb-in	1.5Nm 12 lb-in

Standard Pack: 10

Weight: 1.2kg (2.64 lb.)



Shunt Trip

Shunt Trip and Undervoltage Trip

Description	Shunt Trip Type/Cat. No.	Undervoltage Trip Type/Cat. No.	Cable Max	Cable Min	Torque Max	Torque Min
AC Coil:						
12V AC	FA12ACL	UV12ACL	25mm ² 3 AWG	2.5mm ² 12 AWG	2Nm 17.5 lb-in	1.5Nm 12 lb-in
24V AC	FA24ACL	UV24ACL				
48V AC	FA48ACL	UV48ACL				
60V AC	FA60ACL	UV60ACL				
110V AC	FA110ACL	UV110ACL				
120V AC	FA120ACL	UV120ACL				
230V AC	FA230ACL	UV230ACL				
277V AC	FA277ACL	UV277ACL				
400V AC	FA400ACL	UV400ACL				
DC Coil:						
12V DC	FA12DCL	UV12DCL	25mm ² 3 AWG	2.5mm ² 12 AWG	2Nm 17.5 lb-in	1.5Nm 12 lb-in
24V DC	FA24DCL	UV24DCL				
48V DC	FA48DCL	UV48DCL				
110V DC	FA110DCL	UV110DCL				

Standard Pack: 10

Weight: 1.1kg (2.43 lb.)



Undervoltage Trip

Auxiliary Contact (6A/120VAC; 3A/240VAC)

Description	Type/ Cat. No.	Cable Max	Cable Min	Torque Max	Torque Min
1 x CO	H1COL	2.5mm ² 12 AWG	0.5mm ² 20 AWG	0.5Nm 4 lb-in	0.33Nm 3 lb-in
2 x CO	H2COL				
1 x CO, 1 Signal & Test Button	HSTCOL				

Standard Pack: 15

Weight: 0.5kg (1.32 lb.)



Lock-out Adapter

Description	Type/ Cat. No.
Yellow	EASS2L

Standard Pack: 10

Weight: 50g (1.76 oz.)



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Altech:](#)

[FA230ACL](#) [EASS2L](#) [FA24ACL](#) [FA110DCL](#) [FA24DCL](#) [FA12DCL](#) [FA48DCL](#) [FA12ACL](#) [FA400ACL](#) [ALTN2L](#)
[FA48ACL](#) [EASS2](#) [FA60ACL](#) [FA110ACL](#) [FA120ACL](#) [FA277ACL](#)