

Main

Commercial Status	Commercialised
Range of product	TeSys GS 32...1250
Device short name	Auxiliary early break and signalling contact
Product or component type	Auxiliary contact
Product compatibility	GS 32...1250
Contacts type and composition	1 NO
[Ie] rated operational current	1.4 A at 48 V DC-13 0.55 A at 125 V DC-13 0.27 A at 250 V DC-13 0.15 A at 400 V DC-13 2.8 A at 24 V DC-13 1.8 A at 400 V AC-15 1.5 A at 480 V AC-15 6 A at 120 V AC-15 3 A at 240 V AC-15

Complementary

Fuse type	BS DIN NFC
Mounting location	Front Side
Product weight	0.015 kg

Contractual warranty

Period	18 months
--------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Auxiliary Contacts - 1 N/O



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Schneider Electric:](#)

[GS1AM110](#)