

PIN RECEPTACLES

**FOR .048" - .064" DIAMETER PINS (#13 CONTACT)
FOR .045" - .065" DIAMETER PINS (#23 CONTACT)**

| | | | |
|---|--|---|--|
| <p>0364 0364-0-15-XX-13-XX-10-0 Solder mount in .100 min. mounting hole Also available on 16mm wide carrier tape: 1,300 parts per 13" reel See page 194.13 for Tape & Reel details</p> | <p>0363 0363-0-15-XX-23-XX-10-0 Solder mount in .102 min. mounting hole</p> | <p>0365 0365-0-15-XX-23-XX-10-0 Hex press-fit in .105 plated through-hole Also available on 16mm wide carrier tape: 1,200 parts per 13" reel See page 194.14 for Tape & Reel details</p> | <p>0366 0366-0-15-XX-13-XX-10-0 Press-fit in .109 mounting hole</p> |
| <p>0372 0372-0-15-XX-13-XX-10-0 Solder mount in .102 min. mounting hole Also available on 24mm wide carrier tape: 950 parts per 13" reel See page 194.14 for Tape & Reel details</p> | <p>0362 0362-0-15-XX-X3-XX-10-0 Solder mount in .102 min. mounting hole</p> | <p>0367 0367-0-15-XX-23-XX-10-0 Square press-fit in .040 plated through-hole</p> | <p>9324 9324-0-15-XX-23-XX-04-0 Press-fit in .106 mounting hole</p> |
| <p>0492 0492-0-15-XX-13-XX-04-0 Press-fit in .106 mounting hole</p> | <p>0381 0381-0-15-XX-23-XX-10-0 Press-fit in .104 mounting hole</p> | <p>4034 4034-0-15-XX-23-XX-04-0 Press-fit in .109 mounting hole</p> | <p>3044 3044-0-15-XX-23-XX-04-0 Solder mount in .104 min. mounting hole</p> |

SPECIFICATIONS:

Shell Material: Brass Alloy 360, 1/2 Hard
Contact Material: Beryllium Copper Alloy 172, HT
Dimensions: Inches
Tolerances On: Lengths: ±.005
Diameters: ±.002
Angles: ± 2°



ORDER CODE: XXXX - X - XX - XX - XX - XX - 0

BASIC PART #

SPECIFY SHELL FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 15 10 μ" GOLD OVER NICKEL (RoHS)

SPECIFY CONTACT FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 27 30 μ" GOLD OVER NICKEL (RoHS)

SELECT CONTACT:

#13 or #23 CONTACT (DATA ON PAGE 260)
(For alternate contact choices, see group G on page 248)



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mill-Max:

[3044-0-15-01-23-01-04-0](#) [3044-0-15-01-23-27-04-0](#) [0364-0-15-80-13-27-10-0](#) [0363-0-15-80-23-27-10-0](#) [0362-0-15-80-23-80-10-0](#) [0362-0-15-80-23-27-10-0](#) [0364-0-15-15-13-27-10-0](#) [0366-0-15-01-13-27-10-0](#) [0362-0-15-15-23-14-10-0](#) [0365-0-15-15-23-27-10-0](#) [0364-0-15-01-13-27-10-0](#) [0492-0-15-01-13-01-04-0](#) [0492-0-15-01-13-27-04-0](#) [0381-0-15-01-23-01-10-0](#) [0381-0-15-01-23-27-10-0](#) [0372-0-15-01-13-01-10-0](#) [0372-0-15-01-13-27-10-0](#) [0367-0-15-01-23-01-10-0](#) [0367-0-15-01-23-27-10-0](#) [0366-0-15-01-13-01-10-0](#) [0365-0-15-01-23-01-10-0](#) [0364-0-15-01-13-01-10-0](#) [0363-0-15-01-23-01-10-0](#) [0363-0-15-01-23-27-10-0](#) [0362-0-15-01-23-01-10-0](#) [0362-0-15-01-23-27-10-0](#) [0362-0-15-01-13-01-10-0](#) [0362-0-15-01-13-27-10-0](#) [4034-0-15-80-23-80-04-0](#) [0362-0-15-15-13-27-10-0](#) [0362-0-15-15-23-27-10-0](#) [0363-0-15-15-23-27-10-0](#) [0367-0-15-15-23-27-10-0](#) [0372-0-15-15-13-27-10-0](#) [0381-0-15-15-23-27-10-0](#) [0492-0-15-15-13-27-04-0](#) [3044-0-15-15-23-27-04-0](#) [4034-0-15-15-23-27-04-0](#) [9324-0-15-15-23-27-04-0](#) [4034-0-15-00-00-00-04-0](#) [9324-0-15-00-00-00-04-0](#) [0364-0-15-00-00-00-10-0](#) [0365-0-15-00-00-00-10-0](#) [4034-MOD](#) [0492-0-15-00-00-00-04-0](#) [0366-0-15-00-00-00-10-0](#) [3044-0-15-00-00-00-04-0](#) [0372-0-15-00-00-00-10-0](#) [0381-0-15-00-00-00-10-0](#) [0363-0-15-00-00-00-10-0](#) [0364-0-15-01-13-14-10-0](#) [0492-0-15-01-13-14-04-0](#) [0362-0-15-01-23-14-10-0](#) [0362-0-15-01-13-14-10-0](#) [0365-0-15-80-23-14-10-0](#) [0362-0-15-80-23-14-10-0](#) [0366-0-15-01-13-14-10-0](#) [0364-0-15-80-13-14-10-0](#) [0362-0-15-80-13-14-10-0](#) [0381-0-15-01-23-14-10-0](#) [0381-0-15-80-23-14-10-0](#) [0372-0-15-80-13-14-10-0](#) [0366-0-15-80-13-14-10-0](#) [0492-0-15-80-13-14-04-0](#) [3044-0-15-80-23-14-04-0](#) [3044-0-15-01-23-14-04-0](#) [0372-0-15-01-13-14-10-0](#) [0363-0-15-01-23-14-10-0](#) [0363-0-15-80-23-14-10-0](#) [0367-0-15-80-23-14-10-0](#) [0492-0-15-15-13-14-04-0](#) [0362-0-15-15-13-14-10-0](#) [0364-0-15-15-13-14-10-0](#) [0381-0-15-15-23-14-10-0](#) [9324-0-15-80-23-14-04-0](#) [9324-0-15-01-23-14-04-0](#) [4034-0-15-01-23-14-04-0](#) [4034-0-15-80-23-14-04-0](#)