



FEATURES

- ITE (2nd) and Medical 3rd ed. 1MOPP (primarysecondary) safety approved
- 120W compact high density
- 2" x 4" standard footprint
- High efficiency up to 91%
- Universal AC input with active PFC
- Low profile 1U package
- Convection-cooled operation up to 75W
- RoHS compliant
- UL Class I and II approved (for IT equipment)

DESCRIPTION

The MVAB120 series switching power supplies utilize advanced component and circuit technologies to deliver high efficiency. Designed for Medical, Telecom, and Industrial applications to satisfy 1U height design considerations, the MVAB120 Series measures only 2.0" x 4.0" x 1.35". All models offer universal AC input with active power factor correction (PFC) and compliance to worldwide safety and EMC standards.

3D Models of AC-DC Power Supplies in STEP, IGES, or PDF format Click here

Available now at www.murata-ps.com/en/3d/acdc.html



MVAB120 Series

120W 2" x 4" AC-DC Power Supply Converter

ORDERING GUIDE						
Model Number	Medical Approval ¹	Natural Convection Cooling	Forced Air Cooling	Main Output (V1)		
MVAB120-12	No			101/		
MVAB120-12-01	Yes			12V		
MVAB120-24	No		120W @ 250LFM	24V		
MVAB120-24-01	Yes	7514		24V		
MVAB120-28	No	75W	120W @ 230LFW	28V		
MVAB120-28-01	Yes			20V		
MVAB120-48	No			401/		
MVAB120-48-01	Yes			48V		

INPUT CHARACTERISTICS

Parameter	Conditions	Min.	Тур.	Max.	Units
Input Voltage Operating Range	Single phase	90	120/230	264	Vac
Input voltage operating hange	DC ¹	120		300	Vdc
Input Frequency		47	50/60	63	Hz
Turn-on Input Voltage	Input rising at 75W	76		85	Vac
Turn-off Input Voltage	Input falling at 75W	50			Vac
Input Current	90Vac input, full load			1.9	А
Inrush Current	At 264Vac, at 25°C cold start			75	Apk

OUTPUT CHARACTERISTICS

Model Number	Main Output Voltage (V1)	Load Current	Load Capacitance	Line, Load, Cross Regulation	Typical Efficiency @230Vac full load	
MVAB120-12 MVAB120-12-01	12V	0 to 10.0A	0 to 3300µF	± 2%	88%	
MVAB120-24 MVAB120-24-01	24V	0 to 5.0A	0 to 1000µF	± 2%	90%	
MVAB120-28 MVAB120-28-01	28V	0 to 4.29A	0 to 1000µF	± 2%	90%	
MVAB120-48 MVAB120-48-01	48V	0 to 2.5A	0 to 1000µF	± 2%	91%	

MAIN OUTPUT CHARACTERISTICS (ALL MODELS) Min. Max Units Parameter Conditions **Transient Response** 50% load step, 1A/µsec slew rate ± 5 % MVAB120-12 750 µsec Settling Time to 1% of Nominal MVAB120-24, MVAB120-28, MVAB120-48 500 usec Turn On Delay After application of input power 1 sec **Output Voltage Rise** Monotonic, 0 to 75W 50 msec Setpoint Accuracy 120Vac, 75W, 25°C ± 0.5 % 14 **Output Holdup** Full load msec **Temperature Coefficient** 0.02 %/°C Ripple Voltage & Noise² 1 %

1 Medical versions not designed for DC input voltage.

2 Ripple and noise are measured with 0.1 μ F of ceramic capacitance and 47 μ F of electrolytic capacitance on each of the power supply outputs. The output noise requirements apply over a 0 Hz to 20 MHz bandwidth. A short coaxial cable with 50 Ω scope termination is used.

3 Unless otherwise specified, all readings are taken at 120Vac input and 25°C ambient temperature.





For full details go to www.murata-ps.com/rohs



www.murata-ps.com/support

MVAB120 Series

120W 2" x 4" AC-DC Power Supply Converter

ENVIRONMENTAL CHARACTERIS Parameter	Conditions	Min.	Тур.	Max.	Units
	Conditions	-40	iyp.	85	Unita
Storage Temperature Range	Full load	-40		50	
Operating Temperature Dange	50% load	-10 70			°C
Operating Temperature Range					
	Start up	-20 10		95	%
Departing Humidity	Non-condensing				
Dperating Altitude //TBF	Without derating	-200		3000	m
11BF	Telcordia SR-332 M1C3 25°C	1M			Hours
Shock	Operating, IEC60068-2-27, half-sine 5G, 6ms, 3 times per face, 6 faces	Complies			
DIIUCK	Non-operating, IEC60068-2-27, half-sine, 30G, 18ms, 3 times per face, 6 faces	Complies			
	Operating, IEC60068-2-6, 1.0G, 10-150Hz, 10minutes per axis, on all 3 axes				
libration	Non-operating, IEC60068-2-6, 2.0G, 10-150Hz, 10minutes per axis, on all 3 axes				
Safety	IEC60950-1:2005 (2nd Edition); Am1:2009 UL60950-1 2nd Edition,2011-12-19, CSA C22.2 No. 60950-1-07, EN60950-1:2006 + A11:2009 + A1:2010 + A12:2011 IEC60601-1:2005 + CORR.1(2006) + CORR.2(2007) ANSI/AAMI ES60601-1 (2005+C1:09 + A2:10), CSA-C22.2 No. 60 CE Marking per LVD				
Warranty	2 years				
Outside Dimensions	2.0" x 4.0" x 1.35" (50.8mm x 101.6mm x 34.3mm); 2.0" x 4.0" x 1.41" (50.8mm x 101.6mm x 35.8mm) for medical version				
	MVAB120-12/-01 0.34lbs (155g) typical				
Neight	MVAB120-24/-01, MVAB120-28/-01, MVAB120-48/-01 0.36lbs (162g) typical				

PROTECTION CHARACTERISTICS						
Parameter	Conditions	Min.	Тур.	Max.	Units	
Overvoltage Protection	Latching	110		160	%V1	
Overcurrent Protection	Hiccup mode	105		150	%Amax	
Overtemperature Protection	Auto recovery		Complies			

ISOLATION CHARACTERISTICS						
Parameter	Conditions	Min.	Тур.	Max.	Units	
	Primary to Earth Ground (1M00P)	1500			Vac	
Isolation	Primary to Secondary (2M00P or 1 M0PP)	3000			Vdu	
	Secondary to Earth Ground	500			Vdc	
Leakage Current (under normal conditions)	264Vac, 60Hz, 25°C		500		μA	

EMISSIONS AND IMMUNITY		
Characteristic	Standard	Compliance
Input Current Harmonics	IEC/EN 61000-3-2	Class A
Voltage Fluctuation and Flicker	IEC/EN 61000-3-3	Complies
Conducted Emissions	EN 55022	Class B, Class A (at class II equipment)
	FCC Part 15	Class B, Class A (at class II equipment)
ESD Immunity	IEC/EN 61000-4-2	Level 4, Criterion A
Radiated Field Immunity	IEC/EN 61000-4-3	Level 2, Criterion A
Electrical Fast Transient Immunity	IEC/EN 61000-4-4	Level 3, Criterion A
Surge Immunity	IEC/EN 61000-4-5	Level 3, Criterion A
RF Conducted Immunity	IEC/EN 61000-4-6	Level 2, Criterion A
Magnetic Field Immunity	IEC/EN 61000-4-8	Level 1, Criterion A
Voltage dips, interruptions	IEC/EN 61000-4-11	Level 3, Criterion B

MVAB120 Series

120W 2" x 4" AC-DC Power Supply Converter

PERFORMANCE DATA



















MVAB120 Series

120W 2" x 4" AC-DC Power Supply Converter

EMI CONSIDERATIONS

For optimum EMI performance, the power supply should be mounted to a metal plate grounded to all 4 mounting holes of the power supply. To comply with safety standards, this plate must be properly grounded to protective earth (see mechanical dimension notes). Pre-compliance testing has shown the standalone power supply to comply with EN55022 class A radiated emissions. Radiated emission results vary with system enclosure and cable routing paths.

SAFETY CONSIDERATIONS

- 1. This power supply is a component level power supply intended for use in class I or class II applications. Secondary ground traces need to be suitably isolated from primary ground traces when used in class II applications.
- When the power supply is used in class II equipment, all ground traces and components connected to the primary side are considered primary for spacing and insulation considerations.
- 3. Double pole/neutral fusing (-01 medical versions only).

MECHANICAL DIMENSIONS – MVAB120-12



MVAB120 Series

120W 2" x 4" AC-DC Power Supply Converter



MVAB120 Series

120W 2" x 4" AC-DC Power Supply Converter



MVAB120 Series

120W 2" x 4" AC-DC Power Supply Converter



INPUT/OU	INPUT/OUTPUT CONNECTOR AND SIGNAL SPECIFICATION AND MATING CONNECTORS					
PIN	Description	Mating Housing	Crimp terminal/pins			
Input Connector CN1 : Molex 26-62-4030						
1	AC Neutral	Molex 09-50-8031 with locking ramp	Molex 6838 Series			
3	AC Line					
Spade Connector: #250						
GND Earth Ground						
Output Connector CN2 : Molex 26-60-4060						
1, 2, 3	DC Return	Molex 09-50-8061 with locking ramp Molex 6838 Se				
4, 5, 6	V1					

Murata Power Solutions, Inc.

11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A. ISO 9001 and 14001 REGISTERED



This product is subject to the following operating requirements and the Life and Safety Critical Application Sales Policy. Refer to: <u>http://www.murata-ps.com/requirements/</u>

Murata Power Solutions, Inc. ("Murata") makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Buyer represents and agrees that it has all the necessary expertises to create and implement safeguards that anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm, and take appropriate remedial actions. Buyer will fully indemnify Murata, its affiliated companies, and its representatives against any damages arising out of the use of any Murata products in safety-critical applications. Specifications are subject to change without notice.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata:

<u>MVAB120-12</u> <u>MVAB120-24</u> <u>MVAB120-48</u> <u>MVAB120-12-01</u> <u>MVAB120-28</u> <u>MVAB120-48-01</u> <u>MVAB120-28-01</u> MVAB120-24-01