

Small Signal Transistors

TO-92 Case (Continued)



TYPE NO.	DESCRIPTION	LEAD CODE	V _{CB0}	V _{CEO}	V _{EBO}	I _{CBO} @	V _{CB}	h _{FE}		@V _{CE}	@I _C	V _{CE(SAT)} @ I _C		C _{ob}	f _T	NF	t _{off}
			(V)	(V)	(V)	(nA)		(V)	MIN	MAX	(V)	(mA)	(V)	(mA)	(pF)	(MHz)	(dB)
			MIN	*V _{CES} MIN	MIN	*I _{CES} MAX			*h _{FE} (1kHz)				*C _{rb} MAX	*TYP	MIN	MAX	MAX
PN3641	NPN AMPL/SWITCH	EBC	60	30	5.0	50*	50	40	120	10	150	0.22	150	8.0	150	--	150
PN3642	NPN AMPL/SWITCH	EBC	60	45	5.0	50*	50	40	120	10	150	0.22	150	8.0	150	--	150
PN3643	NPN AMPL/SWITCH	EBC	60	30	5.0	50*	50	100	300	10	150	0.22	150	8.0	250	--	150
PN3644	PNP AMPL/SWITCH	EBC	45	45	5.0	35*	30	100	300	10	150	1.0	300	8.0	200	--	100
PN3645	PNP AMPL/SWITCH	EBC	60	60	5.0	35*	50	100	300	10	150	1.0	300	8.0	200	--	100
PN3646	NPN SAT SWITCH	EBC	40	15	5.0	500*	20	30	120	0.40	30	0.50	300	5.0	350	--	28
PN3694	NPN AMPL/SWITCH	EBC	45	45	4.0	50	30	100	400	10	10	--	--	6.0	200	--	--
PN4033	PNP AMPL/SWITCH	EBC	80	80	5.0	50	60	100	300	5.0	100	0.5	500	20	--	--	50
PN4249	PNP LOW NOISE	EBC	60	60	5.0	10	40	100	300	5.0	0.10	0.25	10	6.0	40	3.0	--
PN4250A	PNP LOW NOISE	EBC	60	60	5.0	10	50	250	700	5.0	0.10	0.25	10	6.0	50	2.0	--
PN4258	PNP SAT SWITCH	EBC	12	12	4.5	10*	6.0	30	120	3.0	10	0.50	50	3.0	700	--	20
PN4274	NPN SAT SWITCH	EBC	30	12	4.5	400*	20	35	120	1.0	10	0.50	100	4.0	400	--	12
PN4275	NPN SAT SWITCH	EBC	40	15	4.5	400*	20	35	120	1.0	10	0.50	100	4.0	400	--	12
PN4354	PNP AMPL/SWITCH	EBC	60	60	5.0	50	50	50	500	10	10	0.50	500	30	100	3.0	400
PN4355	PNP AMPL/SWITCH	EBC	60	60	5.0	50	50	100	400	10	10	1.0	1,000	30	100	3.0	400
PN4356	PNP AMPL/SWITCH	EBC	80	80	5.0	50	50	50	250	10	10	0.50	500	30	100	3.0	400
PN4916	PNP AMPL/SWITCH	EBC	30	30	5.0	25	15	70	200	1.0	10	0.30	50	4.5	400	4.0	--
PN4917	PNP AMPL/SWITCH	EBC	30	30	5.0	25	15	150	300	1.0	10	0.30	50	4.5	450	4.0	--
PN5127	NPN AMPL/SWITCH	EBC	20	12	3.0	50	10	15	300	10	2.0	0.30	10	3.5	150	--	--
PN5128	NPN AMPL/SWITCH	EBC	15	12	3.0	50	10	35	350	10	50	0.25	150	10	150	--	--
PN5129	NPN AMPL/SWITCH	EBC	15	12	3.0	50	10	35	350	10	50	0.25	150	10	--	--	--
PN5130	NPN RF OSC	EBC	30	12	1.0	50	10	15	250	10	8.0	0.60	10	1.7	--	400	--
PN5131	NPN AMPL/SWITCH	EBC	20	15	3.0	50	10	30	50	1.0	10	1.0	10	6.0	100	--	--
PN5132	NPN AMPL/SWITCH	EBC	20	20	3.0	50	10	30	400	10	10	2.0	10	3.5	200	4.0	--
PN5133	NPN LOW NOISE	EBC	20	18	3.0	50	15	60	1,000	5.0	1.0	0.40	1.0	5.0	40	--	--
PN5134	NPN SAT SWITCH	EBC	20	10	3.5	10,000	15	20	150	1.0	10	0.25	10	4.0	--	--	18
PN5135	NPN AMPL/SWITCH	EBC	30	25	4.0	300	15	50	600	10	10	1.0	100	25	40	--	--
PN5136	NPN AMPL/SWITCH	EBC	30	20	3.0	100	20	20	400	1.0	150	0.25	150	35	40	--	--
PN5137	NPN AMPL/SWITCH	EBC	30	20	3.0	100	20	20	400	1.0	150	0.25	150	35	40	--	--
PN5138	PNP AMPL/SWITCH	EBC	30	30	5.0	50	20	50	800	10	0.10	0.30	10	7.0	30	--	--
PN5139	PNP AMPL/SWITCH	EBC	20	20	5.0	50*	15	40	--	1.0	10	0.50	50	5.0	300	--	200
PN5142	PNP AMPL/SWITCH	EBC	20	20	4.0	50*	12	30	--	1.0	50	2.0	300	10	--	--	200
PN5143	PNP AMPL/SWITCH	EBC	20	20	4.0	50*	12	30	--	1.0	50	2.0	300	10	--	--	200
PN5825	NPN AMPL/SWITCH	EBC	50	40	5.0	50	40	100	200	5.0	2.0	0.125	10	4.0	90	--	--
PN5826	NPN AMPL/SWITCH	EBC	50	40	5.0	50	40	150	300	5.0	2.0	0.125	10	4.0	90	--	--
PN5827	NPN AMPL/SWITCH	EBC	50	40	5.0	50	40	250	500	5.0	2.0	0.125	10	4.0	90	--	--
PN5828	NPN AMPL/SWITCH	EBC	50	40	5.0	50	40	400	800	5.0	2.0	0.125	10	4.0	90	--	--
PN5910	PNP SAT SWITCH	EBC	20	20	4.5	10*	10	30	120	0.30	10	0.50	50	3.0	700	--	20
PN6010	NPN AMPL/SWITCH	EBC	50	40	5.0	10	25	100	300	1.0	10	0.50	500	10	105	5.0	400

Devices are available lead formed,
See pages 216 thru 219 for details.
Also available in Ammpack or Tape & Reel,
See pages 230 thru 235 for details.

Central[™]
Semiconductor Corp.
www.centalsemi.com

(1-March 2012)

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Central Semiconductor:](#)

[PN3644](#) [PN4249](#) [PN5139](#) [PN5133](#) [PN5138](#)