

PIN RECEPTACLES

FOR .025" - .037" DIAMETER PINS AND .025" SQUARE PINS

<p>1305 1305-0-15-XX-47-XX-04-0 Press-fit in .061 mounting hole</p>	<p>1306 1306-0-15-XX-47-XX-04-0 Press-fit in .061 mounting hole</p>	<p>7305 7305-0-15-XX-47-XX-10-0 Solder mount in .060 min. mounting hole Also available on 8mm wide carrier tape: 6,000 parts per 13" reel See page 194.9 for Tape & Reel details</p>	<p>0400 0400-0-15-XX-47-XX-04-0 Press-fit in .067 mounting hole</p>
<p>0335 0335-0-15-XX-47-XX-04-0 Hex press-fit in .064 plated through-hole</p>	<p>4614 4614-0-31-XX-47-XX-04-0 Compliant press-fit in .040 ± .003 plated hole. For .060" → .100" thick board</p>	<p>4615 4615-0-31-XX-47-XX-04-0 Compliant press-fit in .040 ± .003 plated hole. For .090" → .130" thick board</p>	<p>7614 7614-0-31-XX-47-XX-04-0 Compliant press-fit in .040 ± .003 plated hole. For .060" → .100" thick board</p>
<p>8401 8401-0-15-XX-47-XX-04-0 Hex press-fit in .063 plated through-hole</p>	<p>2400 2400-0-15-XX-47-XX-04-0 Press-fit in .066 mounting hole</p>	<p>6857 6857-0-15-XX-47-XX-10-0 Press-fit in .062 mounting hole</p>	<p>9393 9393-0-15-XX-47-XX-10-0 Press-fit in .067 mounting hole</p>

SPECIFICATIONS:

Shell Material: Brass Alloy 360, 1/2 Hard
Contact Material: Beryllium Copper Alloy 172, HT
Dimensions: Inches
Tolerances On: Lengths: ±.005
 Diameters: ±.002
 Angles: ± 2°



ORDER CODE: XXXX - X - XX - XX - 47 - XX - XX - 0

BASIC PART #

SPECIFY SHELL FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 15 10 μ" GOLD OVER NICKEL (RoHS)

SPECIFY CONTACT FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 27 30 μ" GOLD OVER NICKEL (RoHS)

SELECT CONTACT:

#47 CONTACT (DATA ON PAGE 256)

(For alternate contact choices, see group D on page 248)



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mill-Max:

[0400-0-15-01-47-01-04-0](#) [8401-0-15-01-47-01-04-0](#) [7614-0-31-01-47-27-04-0](#) [4615-0-31-01-47-01-04-0](#) [4614-0-31-01-47-01-04-0](#) [4614-0-31-01-47-27-04-0](#) [2400-0-15-01-47-01-04-0](#) [2400-0-15-01-47-27-04-0](#) [1306-0-15-01-47-01-04-0](#) [1306-0-15-01-47-27-04-0](#) [1305-0-15-01-47-01-04-0](#) [1305-0-15-01-47-27-04-0](#) [0400-0-15-01-47-27-04-0](#) [0335-0-15-01-47-01-04-0](#) [0335-0-15-01-47-27-04-0](#) [0335-0-15-15-47-27-04-0](#) [0400-0-15-15-47-27-04-0](#) [1305-0-15-15-47-27-04-0](#) [1306-0-15-15-47-27-04-0](#) [2400-0-15-15-47-27-04-0](#) [4614-0-31-15-47-27-04-0](#) [7305-0-15-15-47-27-10-0](#) [0400-0-15-01-47-01-04-0](#) [9393-0-15-00-00-00-10-0](#) [7305-0-15-00-00-00-10-0](#) [0400-0-15-00-00-00-04-0](#) [7614-0-31-00-00-00-04-0](#) [6857-0-15-00-00-00-10-0](#) [1306-0-15-00-00-00-04-0](#) [4615-0-31-00-00-00-04-0](#) [4614-0-31-00-00-00-04-0](#) [0335-0-15-00-00-00-04-0](#) [1305-0-15-00-00-00-04-0](#) [2400-0-15-00-00-00-04-0](#) [7305-0-15-01-47-14-10-0](#) [7305-0-15-15-47-14-10-0](#) [1306-0-15-01-47-14-04-0](#) [2400-0-15-01-47-14-04-0](#) [0335-0-15-01-47-14-04-0](#) [0400-0-15-01-47-14-04-0](#) [1305-0-15-01-47-14-04-0](#) [2400-0-15-80-47-14-04-0](#) [0335-0-15-80-47-14-04-0](#) [1305-0-15-80-47-14-04-0](#) [0400-0-15-80-47-14-04-0](#) [1306-0-15-80-47-14-04-0](#) [0335-0-15-15-47-14-04-0](#) [4614-0-31-15-47-14-04-0](#) [7305-0-15-80-47-14-10-0](#) [6857-0-15-80-47-14-10-0](#) [4614-0-31-01-47-14-04-0](#) [4615-0-31-80-47-14-04-0](#) [4614-0-31-80-47-14-04-0](#) [4615-0-31-01-47-14-04-0](#) [7614-0-31-01-47-14-04-0](#) [9393-0-15-01-47-14-10-0](#) [9393-0-15-80-47-14-10-0](#) [8401-0-15-01-47-14-04-0](#) [6857-0-15-01-47-14-10-0](#) [7614-0-31-80-47-14-04-0](#) [8401-0-15-80-47-14-04-0](#)