

FREQUENCY IN HERTZ


<u>SENSITIVITY</u>			<u>DEVICE CONFORMITY</u>		
<u>FREQUENCY</u>	MIN.	NOM.	<u>MAX.</u>	<u>RANGE OF DEVIATION FROM 3 kHz</u>	
300		-45.0		-1.5 +1.5	
1000	-49.5	-45.0	-40.5	0.0 0.0	
3000		-44.5		- I . 0 + 2 . 0	

NOTES:

I. ALL DATA MEASURED WITH CIRCUIT CONFIGURATION SHOWN BELOW.

2. CASE CONNECTED TO NEGATVE TERMINAL.

DC	BATTERY	"A" WEIGHTED NOISE	OUTPUT IMPEDANCE OHMS (AT I kHz)		
SUPPLY	CURRENT DRAIN	(RE I.O VOLT)	MIN.	NOM. MAX	MAX.
Ι.5V	0.3 mA MAX.	-103 dB MAX.	4900	5200	5500



- X + - I .5 VDC			
DIRECTION OF ACCELERATION <u>TEST_CONDITIONS</u>	Revision C.O. # Implementation Date	RELEASE LEVEL	REVISION
	A MI0101018 2-13-06	Released	A
KNOWLES ELECTRONICS	WHEN TEST LIMITS ARE USED TO ESTABLISH INCOMING IN CRITERIA, CORRELATION OF TEST EQUIPMENT WITH KNOWN ELIMINATION OF EQUIPMENT AND TEST METHOD VARIATION	NSPECTION ACCEPTANCE/REJECTION DR. BY LES IS ALSO REQUIRED FOR MMM N CK. BY	DATE 2 - 1 3 - 0 6 DATE
ITASCA, ILLINOIS U.S.A.	TITLE: VIBRATION TRANSDUCER PERFORMANCE SPECIFICATION	BU-27135-000 G JP SHT 2.1 G JP	2 - 1 5 - 0 6 Date 2 - 1 5 - 0 6

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Knowles: BU-27135-000