



MICRO SWITCH
 FREEPORT ILLINOIS, U.S.A.
 A DIVISION OF HONEYWELL INC.
 FED.MFG.CODE 91929



10.0 AMP CURRENT SENSOR

CATALOG LISTING
CSDD1EG

THIS DRAWING COVERS A PROPRIETARY ITEM AND IS THE PROPERTY OF MICRO SWITCH, A DIVISION OF HONEYWELL. THIS DRAWING IS NOT TO BE COPIED OR USED WITHOUT THE APPROVAL OF MICRO SWITCH.




SUGGESTED HOLE CENTERS
 SCALE 2:1
 COMPONENT SIDE



CHARACTERISTICS	
SUPPLY VOLTAGE	4.5 TO 24 VOLTS
SUPPLY CURRENT	22mA MAX, 16mA TYP
TEMPERATURE	-25 TO 85°C
CURRENT: OPERATING	10.0 AMPS ±5% (@25°C)
RELEASE	7.6 AMPS MIN (@25°C)
MAX CONTINUOUS	20 AMPS
OUTPUT CURRENT	40mA MAX SINK
V _{sat}	.4 VOLTS MAX
RESISTANCE	3 mΩ
INDUCTANCE	3 μH

NOTE
 1 - ELECTRICAL CONNECTIONS INDICATED ON
 BOTTOM OF DEVICE



THIRD ANGLE PROJECTION		
		
SCALE	2:1	
DO NOT SCALE PRINT		
UNLESS OTHERWISE SPECIFIED TOLERANCES ARE		
ONE PLACE	(.0)	±.030
TWO PLACE	(.00)	±.015
THREE PLACE	(.000)	±.005
ANGLES	±	
RAW MATERIAL—COMMERCIAL STANDARD		
WEIGHT		

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Honeywell:](#)

[CSDD1EG](#)