



POS Series 120V 50/60Hz 500VA 300W Standby UPS, Tower, USB port, 6 Outlets, TEL/DSL Protection

MODEL NUMBER: POS500







Description

Tripp Lite's POS500 standby UPS system offers surge suppression and long-lasting battery support, ideal for Kiosks, Point-of-Sale, Network Workstations and standalone PC applications. Special housing with rear-facing outlets fits into limited height and width UPS compartments in kiosks and other equipment housings. Internal UPS circuits maintain AC output during power failures and severe brownout conditions so that connected equipment can be properly shut down without data loss. Includes 3 battery-supported outlets for computer, monitor and one vital system peripheral, plus 3 additional surge suppression-only outlets for printers and other system accessories not requiring battery support. USB port enables optional unattended system shutdown without data loss in case of extended power failure; cable included. HIDcompliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. PowerAlert software available via FREE download. Built-in single line phone suppression protects modem, fax machine or other peripheral with a standard dialup/DSL phone connection. Built-in audible alarm and 5 LEDs indicate line power status, battery power status, battery low/replace, overload and site wiring fault status. 500VA/300W power handling ability supports point-ofsale equipment, kiosks, network workstations, small business phone systems and desktop PC equipment. Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application/OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications. Offers 4.9 minutes battery runtime with a full load of 500VA and 15.8 minutes with a half load of 250VA. Supports user battery replacement via built-in access panel. \$150,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only).

Features

 POS500 offer surge suppression and long-lasting battery support for Kiosks, Point-of-Sale, Network Workstations and standalone PC applications

Highlights

- 500VA low-profile tower 120V standby UPS
- Maintains AC output during power failures
- 3 UPS battery supported outlets,
 3 surge-only outlets
- USB port, TEL/DSL protection, 99% efficient
- NEMA 5-15P input and 6 NEMA 5-15R outlets
- This product is ENERGY STAR qualified for its ability to save customers money while helping to protect the environment

Package Includes

 POS500 UPS, USB cable, User manual with warranty information



- Special housing with short 6.54 inch height, thin 3.58 inch width and rear-facing outlets is compatible
 with UPS compartments in many kiosks and other equipment housings
- Supports a full load of 500VA/300 watts for 4.9 minutes and a half load of 250VA/150 watts for 15.8 minutes
- Supplies battery-derived AC output from UPS supported outlets during brownouts, overvoltages and blackout conditions
- Includes 6 total outlets, 3 with UPS and surge suppression for vital system components and 3 with surge suppression only for accessories not requiring battery support
- Compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application/OS or hard power off/on reboot of connected equipment - ideal for unattended kiosk applications
- USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- Built-in single line phone suppression protects modem, fax machine or other peripheral with a standard dialup/DSL phone connection
- Built-in audible alarm and 5 LEDs indicate line power status, battery power status, battery low/replace, overload and site wiring fault status
- Optional <u>PDUB15</u> bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment
- Supports hot swappable, user battery replacement via built-in access panel

Specifications

OUTPUT		
Output Volt Amp Capacity (VA)	500	
Output Watt Capacity (Watts)	300	
Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Nominal Voltage Details	115v nominal output in battery mode	
Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	Automatic frequency selection	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Output Receptacles	(6) 5-15R	
UPS Output Receptacles (Surge Suppression Only)	3 UPS outlets, 3 surge-only outlets	
Hot-Swap PDU options	PDUB15 (2U / 8 5-15R outlets)	





Output AC Waveform (Battery Mode) INPUT Rated input current (Maximum Load) 10A Nominal Input Voltage(s) Supported 120V AC UPS Input Cord Length (tt.) 10A UPS Input Cord Length (tt.) 10B Recommended Electrical Service 15A 120V Input Phase BATTERY Full Load Runtime (min.) 1.8. min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Access Battery A	Output AC Waveform (AC Mode)	Sine wave		
INPUT Rated input current (Maximum Load) 10A Nominal Input Voltage(e) Supported 12DV AC UPS Input Connection Type 5-15P Input Circuit Breakers 10A UPS Input Cord Length (ft.) 6 UPS Input Cord Length (ft.) 7 UPS AC Suppression Joule Rating (ft.) 7 UPS AC Suppression Response 1 (ft.) 7 Input Phase 10 Inpu		Sine wave		
Reted input current (Maximum Load) 10A Nominal Input Voltage(s) Supported 120V AC UPS Input Cornection Type 5-15P Input Circuit Breakers 10A UPS Input Cord Length (ft.) 6 UPS Input Cord Length (m) 1.8 Recommended Electrical Service 15A 120V Input Phase Single-Phase BATTERY Full Load Runtime (min.) 4.9 min. (300w) Half Load Runtime (min.) 15.8 min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Less than 10 hours from 10% to 90% Battery Access Battery Access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & Controls Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDS (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION <td>Mode)</td> <td>PWM sine wave</td>	Mode)	PWM sine wave		
Nominal Input Voltage(s) Supported UPS Input Connection Type 5-15P Input Circuit Breakers 10A UPS Input Cord Length (ft.) 6 UPS Input Cord Length (ft.) 6 UPS Input Cord Length (ft.) 1.8 Recommended Electrical Service 15A 120V Input Phase Single-Phase BATTERY Full Load Runtime (min.) 4.9 min. (300w) Haif Load Runtime (min.) 15.8 min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batter)attrices Battery Access Battery Replacement Battery Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible Alarm Audible alarm indicates power-failure LED Indicators LED Indicators Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating Instantaneous Instantaneous Instantaneous Instantaneous	INPUT			
UPS Input Connection Type 5-15P Input Circuit Breakers 10A UPS Input Cord Length (It.) 6 UPS Input Cord Length (It.) 18 Recommended Electrical Service 15A 120V Input Phase Single-Phase BATTERY Full Load Runtime (min.) 4.9 min. (300w) Half Load Runtime (min.) 15.8 min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 28651 Battery Access Battery Access Battery Access 48 Battery Access Battery Combination switch controls on/off power status and self-test operation Audible Alarm Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDS (online, on battery, replace battery, overload) Surger / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 Instantaneous	Rated input current (Maximum Load)	10A		
Input Circuit Breakers 10A UPS Input Cord Length (It.) 6 UPS Input Cord Length (Im) 1.8 Recommended Electrical Service 15A 120V Input Phase Single-Phase BATTERY Full Load Runtime (min.) 4.9 min. (300w) Half Load Runtime (min.) 15.8 min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Replacement Battery 2 Battery Replacement Battery 2 Battery Access Battery Access Battery Access Battery Access Battery Replacement Description Not-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & COMBINATION OF Modified Plant Indicates power-failure LED Indicators 4 LEDS (online, on battery, replace battery, overfoad) Site Wiring Fault Indication Response Time Instanteous Instantaneous Instanteous Instantaneous Instantaneous Instantaneous Instantaneous Instantaneous Instantaneous Instantaneous INSTANC Suppression Response Instantaneous Instant	Nominal Input Voltage(s) Supported	120V AC		
UPS Input Cord Length (ft.) 6 UPS Input Cord Length (m) 1.8 Recommended Electrical Service 15A 120V Input Phase Single-Phase BATTERY Full Load Runtime (min.) 4.9 min. (300w) Half Load Runtime (min.) 15.8 min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & COWNOLLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overfoad) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous Instantaneous	UPS Input Connection Type	5-15P		
UPS Input Cord Length (m) Recommended Electrical Service Input Phase Single-Phase BATTERY Full Load Runtime (min.) 4.9 min. (300w) Half Load Runtime (min.) 15.8 min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery) Catrifuge Rattery Access Battery Access Battery Access Battery Access Battery Access Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTOLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) SIRGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating LISSAN Compression Response Linetantaneous	Input Circuit Breakers	10A		
Recommended Electrical Service 15A 120V Input Phase Single-Phase BATTERY Full Load Runtime (min.) 4.9 min. (300w) Half Load Runtime (min.) 15.8 min. (150w) DC System Voltage (VDC) 12 Battery Recharge Rate (Included atteries) Battery Recharge Rate (Included atteries) Battery Recharge Rate (Included atteries) Battery Access Battery access door Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous	UPS Input Cord Length (ft.)	6		
BATTERY Full Load Runtime (min.)	UPS Input Cord Length (m)	1.8		
BATTERY Full Load Runtime (min.)	Recommended Electrical Service	15A 120V		
Full Load Runtime (min.) 4.9 min. (300w) Half Load Runtime (min.) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery) Cartridge RBC51 Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wirring Fault Indication Rear panel site wirring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time 480	Input Phase	Single-Phase		
Half Load Runtime (min.) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery) Cartridge Battery Access Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Time 12 Instantaneous	BATTERY			
Half Load Runtime (min.) DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery Recharge Rate (Included Batter) Internal UPS Replacement Battery Cartridge Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Time Instantaneous	Full Load Runtime (min.)	4.9 min. (300w)		
Battery Recharge Rate (Included Batteries) Internal UPS Replacement Battery Cartridge Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wirring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Time Instantaneous	Half Load Runtime (min.)			
Batteries) RBC51 Battery Access Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No WSER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Time RBC51 Battery Access Battery access door Hot-swappable, user replaceable batteries Expandable Patteries Surger Interpretation Audible alarm indicates power-failure 4 LEDs (online, on battery, replace battery, overload) Surger / Noise Suppression Instantaneous Instantaneous	DC System Voltage (VDC)	12		
Cartridge Battery Access Battery access door Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	Battery Recharge Rate (Included Batteries)	Less than 10 hours from 10% to 90%		
Battery Replacement Description Hot-swappable, user replaceable batteries Expandable Runtime No USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous	Internal UPS Replacement Battery Cartridge	<u>RBC51</u>		
USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous	Battery Access	Battery access door		
Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous	Battery Replacement Description	Hot-swappable, user replaceable batteries		
Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous	Expandable Runtime	No		
Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous	USER INTERFACE, ALERTS & CONTROLS			
LED Indicators 4 LEDs (online, on battery, replace battery, overload) Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous				
Site Wiring Fault Indication Rear panel site wiring fault LED SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 480 UPS AC Suppression Response Instantaneous	Audible Alarm	Audible alarm indicates power-failure		
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	LED Indicators	4 LEDs (online, on battery, replace battery, overload)		
UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	Site Wiring Fault Indication	Rear panel site wiring fault LED		
UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	SURGE / NOISE SUPPRESSION			
UPS AC Suppression Response Time Instantaneous		480		
UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out)	UPS AC Suppression Response			
	UPS Dataline Suppression	1 line TEL/DSL (1 in / 1 out)		
EMI / RFI AC Noise Suppression Yes	EMI / RFI AC Noise Suppression	Yes		



PHYSICAL		
Installation Form Factors Supported with Included Accessories	Tower	
Primary Form Factor	Tower	
UPS Power Module Dimensions (hwd, in.)	6.5 x 3.6 x 11.2	
UPS Power Module Dimensions (hwd, cm)	16.51 x 9.14 x 28.45	
UPS Power Module Weight (lbs.)	8.1	
UPS Power Module Weight (kg)	3.67	
UPS Shipping Dimensions (hwd / in.)	9.4 x 7.1 x 14.2	
UPS Shipping Dimensions (hwd / cm)	23.88 x 18.03 x 36.07	
Shipping Weight (lbs.)	10.5	
Shipping Weight (kg)	4.8	
UPS Housing Material	ABS	
Primary UPS Height (mm)	165	
Primary UPS Width (mm)	91	
Primary UPS Depth (mm)	284	
Shipping Height (mm)	239	
Shipping Width (mm)	180	
Shipping Depth (mm)	361	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	10	
Battery Mode BTU / Hr. (Full Load)	195	
AC Mode Efficiency Rating (100% Load)	99%	
COMMUNICATIONS		
Communications Interface	USB (HID enabled)	
PowerAlert Software	For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at http://www.tripplite.com/poweralert	
Communications Cable	USB interface cable included	





WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications		
Network UPS Tools Compatibility	NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at http://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite		
LINE / BATTERY TRANSFER			
Transfer Time	4 milliseconds from AC to battery mode; 4 milliseconds from battery to AC mode		
Low Voltage Transfer to Battery Power (Setpoint)	93		
High Voltage Transfer to Battery Power (Setpoint)	139		
SPECIAL FEATURES			
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
High Availability UPS Features	Hot swappable batteries		
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS		
CERTIFICATIONS			
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category B (EMI); ENERGY STAR Qualified		
WARRANTY			
Product Warranty Period (Worldwide)	2-year limited warranty		
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$150,000 Ultimate Lifetime Insurance		

© 2017 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite: POS500