

APPLICATOR PARTS LIST				TYPE			SPECIAL		
				LENGTHWISE		CONTACT		AMP INCORPORATED FLAT WIRE HARRISBURG, PENNA.	
NO.	DESCRIPTION	REQ.	PART NO.	NO.	DESCRIPTION	REQ.	PART NO.	CRIMPING DATA	TERMINALS
1	WIRE CRIMPER	1	693800-1	42				TO APPLY TERMINAL	61462-
2	INS. CRIMPER			43					
3	ANVIL	1	693802-1	44	HOLD DOWN (STRIP)	1	375826	WIRE SIZE	CRIMP HEIGHT
4	ANVIL SPACER			45				18	.071±.002
5	SHEAR BLADE	1	465233-2	46				22	.061±.002
6	REAR SHEAR PLATE	1	385013-4	47					
7	SHEAR BLADE SPACER	2	370954	48					
8	FRONT SHEAR PLATE	1	371832	49	HOLD DOWN (BLADE ME)	1	811065-1		
9	REAR ANVIL SPACER PLT.	1	1-473801-2	50					
10	FRONT ANVIL SPACER PLT.			51				CRIMP	SIZE
11	TOOL SPACER	1	371354	52				WIRE	.120 F
12	CRIMP SPACER			53				INSUL.	BLUNT
13	FRONT STRIP GUIDE	1	373285	54				SLEEVED	
14	REAR STRIP GUIDE	1	373285	55				INSULATION RANGE	WIRE RANGE
				56	FLOATING WIRE STOP	1	565281-2	.085 THK.	22-18
15	RAM	1	471911	57	BUSHING	Δ	REF 811259-2	EXPLODED VIEW	3M
16	TOOL HOLDER			58	STOP	Δ	REF 811259-2	A-6000 A-6000-1	5-14
17	ADJ. CRIMP MOUNT			59	SPACER	Δ	REF 811260-1	REMARKS	
18	ADJ. BLOCK			60	SLIDE	Δ	REF 811260-1	Δ DENOTE PARTS OF	
19	APPLICATOR MOUNT ASSY.	1	570656	61	MOUNT	Δ	REF 811260-1	565081-4 ASSY (ITEM 56)	
20	BASE PLATE			62				(MAGNETIC PICKUP WIRE	
21	BASE BLOCK			63	HOLDER MAGNET	Δ	REF 811284-1	STOP)	
22	STRIP GUIDE PLATE			64	BRACKET SLIDE	Δ	REF 811285-1	2. SET UP WITH	
23	ANVIL HOLDER	1	370526	65				CUSTOMER WIRE.	
24	AUX. ANVIL HOLDER	1	377515						
25	STRIPPER			66	MAGNET	Δ	REF 811287-1		
26	STRIPPER MOUNT	Δ	REF 811323-1	67	WIRE STOP	Δ	REF 465344-3		
27	RETAINER PLATE	Δ	REF 372251	68					
28	STRIPPER MOUNT BRACKET			69	MECH. FEED	1	374999		
29	STRIPPER BUSHING			70	TENSION ADJ. PLATE	1	374999		
30	STOCK DRAG	1	375381	71	LUBRICATOR ASSY	1	465189-2		
31	STOCK DRAG HANDLE			72	SYNTHETIC OIL	1	22019-1		
32	STOCK DRAG STUD	2	354045-11						
33	STOCK DRAG SPRING	2	1-23847-1	REV.	REVISION RECORD	DATE	BY	ECN	
34	STOCK DRAG ADJ. SCREW	2	372997	A	SUPERSCREWS -1	3-27-73	AL		
35	FEED FINGER HOLDER			B	REV PER GEN	6-25-73	AL	6-25-73	
36	FEED FINGER	1	375093	C	REV ITEM #40	3-17-75	AL	6-25-73	
37	FEED FINGER TIP			C1	REVISED	3-22-78	AL	6-25-73	
38	FEED FINGER SPACER			C2	ORBS A-281890	2-20-80	AL		
39	BASE CASTING	1	570238	D	REACT 0150-4361-93	3-93	AL		
40	GUARD	1	457664-6	D1	0150-6407-95	9-95	AL		
41				D1	0150-8254-98	1-98	AL		

THIS DRAWING IS A CONTROLLING DOCUMENT FOR AMP INC. IT IS SUBJECT TO CHANGE AND THE CONTROLLING ENGINEERING ORGANIZATION SHOULD BE CONTACTED FOR THE LATEST REVISION.

Δ DENOTES WEARING PARTS RECOMMEND PURCHASE REPLACEMENT

THIS APPLICATOR IS TO BE USED ON AMP-ELECTRIC 1-471293-3

AMP-ELECTRIC MECH. FEED

ALIGN. GA. 679597-1

SERIAL NO. DATE SHIPPED

CUSTOMER NAME AND ADDRESS

APPLICATOR NUMBER 565922-2

REV. 565922-2

SHEET 1 OF 1

FOR HARDWARE
SEE 2-687500-4

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[TE Connectivity:](#)

[565922-2](#)