



**Full - Bridge
Trench + Field Stop IGBT3
Power Module**
 $V_{CES} = 600V$
 $I_C = 75A @ T_c = 80^\circ C$

Application

- Welding converters
- Switched Mode Power Supplies
- Uninterruptible Power Supplies
- Motor control

Features

- **Trench + Field Stop IGBT3**
 - Low voltage drop
 - Low tail current
 - Switching frequency up to 20 kHz
 - Low leakage current
 - RBSOA and SCSOA rated
- Kelvin emitter for easy drive
- Very low stray inductance
- High level of integration
- Internal thermistor for temperature monitoring



All multiple inputs and outputs must be shorted together

Example: 13/14 ; 29/30 ; 22/23 ...

Benefits

- Stable temperature behavior
- Very rugged
- Solderable terminals for easy PCB mounting
- Direct mounting to heatsink (isolated package)
- Low junction to case thermal resistance
- Easy paralleling due to positive TC of V_{CESat}
- Low profile
- Each leg can be easily paralleled to achieve a phase leg of twice the current capability
- RoHS compliant

All ratings @ $T_j = 25^\circ C$ unless otherwise specified
Absolute maximum ratings (per IGBT)

Symbol	Parameter	Max ratings	Unit
V_{CES}	Collector - Emitter Voltage	600	V
I_C	Continuous Collector Current	$T_c = 25^\circ C$	A
		$T_c = 80^\circ C$	
I_{CM}	Pulsed Collector Current	$T_c = 25^\circ C$	140
V_{GE}	Gate – Emitter Voltage	± 20	V
P_D	Power Dissipation	$T_c = 25^\circ C$	250
RBSOA	Reverse Bias Safe Operating Area	$T_j = 150^\circ C$	150A @ 550V

 **CAUTION:** These Devices are sensitive to Electrostatic Discharge. Proper Handling Procedures Should Be Followed.

Electrical Characteristics (per IGBT)

Symbol	Characteristic	Test Conditions		Min	Typ	Max	Unit
I_{CES}	Zero Gate Voltage Collector Current	$V_{GE} = 0V$	$V_{CE} = 600V$			250	μA
$V_{CE(sat)}$	Collector Emitter Saturation Voltage	$V_{GE} = 15V$	$T_j = 25^\circ C$		1.5	1.9	V
		$I_C = 75A$	$T_j = 150^\circ C$		1.7		
$V_{GE(th)}$	Gate Threshold Voltage	$V_{GE} = V_{CE}$	$I_C = 600\mu A$	5.0	5.8	6.5	V
I_{GES}	Gate – Emitter Leakage Current	$V_{GE} = 20V$	$V_{CE} = 0V$			600	nA

Dynamic Characteristics (per IGBT)

Symbol	Characteristic	Test Conditions		Min	Typ	Max	Unit
C_{ies}	Input Capacitance	$V_{GE} = 0V$ $V_{CE} = 25V$ $f = 1MHz$		4620			pF
C_{oes}	Output Capacitance			300			
C_{res}	Reverse Transfer Capacitance			140			
$T_{d(on)}$	Turn-on Delay Time	$V_{GE} = \pm 15V$ $V_{CE} = 300V$ $I_C = 75A$ $R_G = 4.7\Omega$	Inductive Switching (25°C)	110			ns
T_r	Rise Time			45			
$T_{d(off)}$	Turn-off Delay Time			200			
T_f	Fall Time			40			
$T_{d(on)}$	Turn-on Delay Time	$V_{GE} = \pm 15V$ $V_{CE} = 300V$ $I_C = 75A$ $R_G = 4.7\Omega$	Inductive Switching (150°C)	120			ns
T_r	Rise Time			50			
$T_{d(off)}$	Turn-off Delay Time			250			
T_f	Fall Time			60			
E_{on}	Turn-on Switching Energy	$V_{GE} = \pm 15V$ $V_{CE} = 300V$ $I_C = 75A$ $R_G = 4.7\Omega$	$T_j = 25^\circ C$	0.35			mJ
E_{off}	Turn-off Switching Energy		$T_j = 150^\circ C$	0.6			
			$T_j = 25^\circ C$	2.2			mJ
			$T_j = 150^\circ C$	2.6			
R_{thJC}	Junction to Case Thermal Resistance					0.6	°C/W

Reverse diode ratings and characteristics (per diode)

Symbol	Characteristic	Test Conditions		Min	Typ	Max	Unit	
V_{RRM}	Peak Repetitive Reverse Voltage					600	V	
I_{RM}	Reverse Leakage Current	$V_R = 600V$				250	μA	
I_F	DC Forward current		$T_C = 40^\circ C$		75		A	
V_F	Diode Forward Voltage	$I_F = 75A$	$T_j = 25^\circ C$		1.6	2	V	
		$V_{GE} = 0V$	$T_j = 150^\circ C$		1.5			
t_{rr}	Reverse Recovery Time	$I_F = 75A$ $V_R = 300V$ $di/dt = 2000A/\mu s$	$T_j = 25^\circ C$		100		ns	
			$T_j = 150^\circ C$		150			
Q_{rr}	Reverse Recovery Charge		$T_j = 25^\circ C$		3.6		μC	
			$T_j = 150^\circ C$		7.6			
E_r	Reverse Recovery Energy		$T_j = 25^\circ C$		0.85		mJ	
			$T_j = 150^\circ C$		1.8			
R_{thJC}	Junction to Case Thermal Resistance					0.98	°C/W	


Temperature sensor NTC (see application note APT0406 on www.microsemi.com for more information).

Symbol	Characteristic		Min	Typ	Max	Unit
R ₂₅	Resistance @ 25°C			50		kΩ
ΔR ₂₅ /R ₂₅				5		%
B _{25/85}	T ₂₅ = 298.15 K			3952		K
ΔB/B		T _C =100°C		4		%








$$R_T = \frac{R_{25}}{\exp\left[B_{25/85}\left(\frac{1}{T_{25}} - \frac{1}{T}\right)\right]} \quad \begin{matrix} T: \text{Thermistor temperature} \\ R_T: \text{Thermistor value at } T \end{matrix}$$




Thermal and package characteristics

Symbol	Characteristic		Min	Max	Unit
V _{ISOL}	RMS Isolation Voltage, any terminal to case t =1 min, 50/60Hz		4000		V
T _J	Operating junction temperature range		-40	175	
T _{JOP}	Recommended junction temperature under switching conditions		-40	T _{Jmax} -25	°C
T _{STG}	Storage Temperature Range		-40	125	
T _C	Operating Case Temperature		-40	125	
Torque	Mounting torque	To heatsink M4	2	3	N.m
Wt	Package Weight			110	g

Package outline (dimensions in mm)

 See application note 1906 - Mounting Instructions for SP3F Power Modules on www.microsemi.com

Typical Performance Curve





DISCLAIMER

The information contained in the document (unless it is publicly available on the Web without access restrictions) is PROPRIETARY AND CONFIDENTIAL information of Microsemi and cannot be copied, published, uploaded, posted, transmitted, distributed or disclosed or used without the express duly signed written consent of Microsemi. If the recipient of this document has entered into a disclosure agreement with Microsemi, then the terms of such Agreement will also apply. This document and the information contained herein may not be modified, by any person other than authorized personnel of Microsemi. No license under any patent, copyright, trade secret or other intellectual property right is granted to or conferred upon you by disclosure or delivery of the information, either expressly, by implication, inducement, estoppels or otherwise. Any license under such intellectual property rights must be approved by Microsemi in writing signed by an officer of Microsemi.

Microsemi reserves the right to change the configuration, functionality and performance of its products at anytime without any notice. This product has been subject to limited testing and should not be used in conjunction with life-support or other mission-critical equipment or applications. Microsemi assumes no liability whatsoever, and Microsemi disclaims any express or implied warranty, relating to sale and/or use of Microsemi products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. Any performance specifications believed to be reliable but are not verified and customer or user must conduct and complete all performance and other testing of this product as well as any user or customers final application. User or customer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the customer's and user's responsibility to independently determine suitability of any Microsemi product and to test and verify the same. The information contained herein is provided "AS IS, WHERE IS" and with all faults, and the entire risk associated with such information is entirely with the User. Microsemi specifically disclaims any liability of any kind including for consequential, incidental and punitive damages as well as lost profit. The product is subject to other terms and conditions which can be located on the web at <http://www.microsemi.com/legal/tnc.asp>

Life Support Application

Seller's Products are not designed, intended, or authorized for use as components in systems intended for space, aviation, surgical implant into the body, in other applications intended to support or sustain life, or for any other application in which the failure of the Seller's Product could create a situation where personal injury, death or property damage or loss may occur (collectively "Life Support Applications").

Buyer agrees not to use Products in any Life Support Applications and to the extent it does it shall conduct extensive testing of the Product in such applications and further agrees to indemnify and hold Seller, and its officers, employees, subsidiaries, affiliates, agents, sales representatives and distributors harmless against all claims, costs, damages and expenses, and attorneys' fees and costs arising, directly or indirectly, out of any claims of personal injury, death, damage or otherwise associated with the use of the goods in Life Support Applications, even if such claim includes allegations that Seller was negligent regarding the design or manufacture of the goods.

Buyer must notify Seller in writing before using Seller's Products in Life Support Applications. Seller will study with Buyer alternative solutions to meet Buyer application specification based on Sellers sales conditions applicable for the new proposed specific part.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Microsemi:](#)

[APTGT75H60T3G](#)