

Is Now Part of



# **ON Semiconductor**®

# To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (\_), the underscore (\_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (\_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at <a href="mailto:www.onsemi.com">www.onsemi.com</a>. Please email any questions regarding the system integration to <a href="mailto:Fairchild\_questions@onsemi.com">Fairchild\_questions@onsemi.com</a>.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or unavteries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or i, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor and is officers, employees, uniotificated use, even if such claim any manner.



## P-Channel PowerTrench<sup>®</sup> MOSFET

## -30 V, -122 A, 3.2 mΩ

## Features

- Max  $r_{DS(on)}$  = 3.2 m $\Omega$  at  $V_{GS}$  = -10 V,  $I_D$  = -21.1 A
- Max  $r_{DS(on)}$  = 5.0 m $\Omega$  at V<sub>GS</sub> = -4.5 V, I<sub>D</sub> = -15.7 A
- Advanced Package and Silicon combination for low r<sub>DS(on)</sub>
- HBM ESD Protection Level of 8kV Typical(Note 3)
- MSL1 Robust Package Design
- RoHS Compliant




## **General Description**

The FDMS6681Z has been designed to minimize losses in load switch applications. Advancements in both silicon and package technologies have been combined to offer the lowest  $r_{DS(on)}$  and ESD protection.

## Applications

- Load Switch in Notebook and Server
- Notebook Battery Pack Power Management



## MOSFET Maximum Ratings T<sub>A</sub> = 25 °C unless otherwise noted.

Symbol	Parar	neter		Ratings	Units
V <sub>DS</sub>	Drain to Source Voltage			-30	V
V <sub>GS</sub>	Gate to Source Voltage			±25	V
I <sub>D</sub>	Drain Current -Continuous	T <sub>C</sub> = 25 °C	(Note5)	-122	
	-Continuous	T <sub>C</sub> = 100 °C	(Note5)	-77	А
	-Continuous	T <sub>A</sub> = 25 °C	(Note 1a)	-21.1	A
	-Pulsed		(Note4)	-600	
P <sub>D</sub>	Power Dissipation	T <sub>C</sub> = 25 °C		73	w
	Power Dissipation	T <sub>A</sub> = 25 °C	(Note 1a)	2.5	vv
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Junction Tempe	rature Range		-55 to +150	°C

## **Thermal Characteristics**

$R_{ ext{ heta}JC}$	Thermal Resistance, Junction to Case	1.7	°C/W
$R_{ ext{ heta}JA}$	Thermal Resistance, Junction to Ambient (Note 1	a) 50	C/VV

## Package Marking and Ordering Information


Device Marking	Device	Package	Reel Size	Tape Width	Quantity
FDMS6681Z	FDMS6681Z	Power 56	13 "	12 mm	3000 units

June 2015

	Parameter	Test Conditions	Min.	Тур.	Max.	Units
Off Chara	octeristics					
BV <sub>DSS</sub>	Drain to Source Breakdown Voltage	I <sub>D</sub> = -250 μA, V <sub>GS</sub> = 0 V	-30			V
$\frac{\Delta BV_{DSS}}{\Delta T_J}$	Breakdown Voltage Temperature Coefficient	$I_D = -250 \ \mu$ A, referenced to 25 °C		20		mV/°C
I <sub>DSS</sub>	Zero Gate Voltage Drain Current	$V_{DS} = -24 \text{ V}, V_{GS} = 0 \text{ V}$			-1	μΑ
I <sub>GSS</sub>	Gate to Source Leakage Current	$V_{GS} = \pm 25 \text{ V}, V_{DS} = 0 \text{ V}$			±10	μA
On Chara	cteristics					
V <sub>GS(th)</sub>	Gate to Source Threshold Voltage	$V_{GS} = V_{DS}, I_{D} = -250 \ \mu A$	-1	-1.7	-3	V
$\frac{\Delta V_{\text{GS(th)}}}{\Delta T_{\text{J}}}$	Gate to Source Threshold Voltage Temperature Coefficient	$I_D$ = -250 $\mu A,$ referenced to 25 °C		-7		mV/°C
	· · ·	V <sub>GS</sub> = -10 V, I <sub>D</sub> = -22.1 A		2.7	3.2	
r <sub>DS(on)</sub>	Static Drain to Source On Resistance	V <sub>GS</sub> = -4.5 V, I <sub>D</sub> = -15.7 A		4.0	5.0	mΩ
		$V_{GS}$ = -10 V, I <sub>D</sub> = -22.1 A, T <sub>J</sub> = 125 °C		3.9	5.0	
9 <sub>FS</sub>	Forward Transconductance	V <sub>DD</sub> = -10 V, I <sub>D</sub> = -22.1 A		143		S
Dynamic	Characteristics					
C <sub>iss</sub>	Input Capacitance			7803	10380	pF
C <sub>oss</sub>	Output Capacitance	<sup>ー</sup> V <sub>DS</sub> = -15 V, V <sub>GS</sub> = 0 V, – f = 1 MHz		1540	2050	pF
C <sub>rss</sub>	Reverse Transfer Capacitance			1345	2020	pF
t <sub>d(on)</sub> t <sub>r</sub> t <sub>d(off)</sub>	Turn-On Delay Time Rise Time Turn-Off Delay Time	$V_{DD}$ = -15 V, I <sub>D</sub> = -22.1 A, V <sub>GS</sub> = -10 V, R <sub>GEN</sub> = 6 Ω		15 38 260	24 61 416	ns ns ns
t <sub>f</sub>	Fall Time			197	316	ns
Q <sub>g</sub>	Total Gate Charge	V <sub>GS</sub> = 0 V to -10 V		172	241	nC
Q <sub>g</sub>	Total Gate Charge	$V_{GS} = 0 V \text{ to } -5 V$ $V_{DD} = -15 V,$		97	136	nC
Q <sub>gs</sub>	Gate to Source Charge	$I_{\rm D} = -22.1  {\rm A}$		22		nC
Q <sub>gd</sub>	Gate to Drain "Miller" Charge			46		nC
•	urce Diode Characteristics		1	1	4	
V <sub>SD</sub>	Source to Drain Diode Forward Voltage	$V_{GS} = 0 V, I_{S} = -2.1 A$ (Note 2)		0.68	1.2	V
50		$V_{GS} = 0 V, I_S = -22.1 A$ (Note 2)		0.79	1.25	V
t <sub>rr</sub>	Reverse Recovery Time	- I <sub>F</sub> = -22.1 A, di/dt = 100 A/μs		44	71	ns
Q <sub>rr</sub>	Reverse Recovery Charge			39	63	nC


00000

Pulse Test: Pulse Width < 300 μs, Duty cycle < 2.0%.</li>
The diode connected between the gate and source serves only as protection against ESD. No gate overvoltage rating is implied.
Pulsed Id please refer to Fig 12 SOA graph for more details.
Computed continuous current limited to Max Junction Temperature only, actual continuous current will be limited by thermal electro-mechanical application board design.





©2009 Fairchild Semiconductor Corporation FDMS6681Z Rev.1.4





©2009 Fairchild Semiconductor Corporation FDMS6681Z Rev.1.4





obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products. FDMS6681Z P-Channel PowerTrench<sup>®</sup> MOSFET



#### TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

AccuPower <sup>TM</sup> AttitudeEngine <sup>TM</sup> Awinda <sup>®</sup> AX-CAP <sup>®*</sup> Bislic TM Build it Now <sup>TM</sup> CorePLUS <sup>TM</sup> CorePOWER <sup>TM</sup> CORPOWER <sup>TM</sup> CROSSVOLT <sup>TM</sup> CTL <sup>TM</sup> CUTRED <sup>®</sup> Dual Cool <sup>TM</sup> ECOSPARK <sup>®</sup> EfficentMax <sup>TM</sup> ESBC <sup>TM</sup> Fiscrichild <sup>®</sup> Fairchild <sup>®</sup> Fairch	F-PFS™ FRFET® Global Power Resource <sup>SM</sup> Green FPS™ Green FPS™ e-Series™ Gmax™ GTO™ IntelliMAX™ ISOPLANAR™ Marking Small Speakers Sound Louder and Better™ MegaBuck™ MICROCOUPLER™ MicroPak™ MicroPak™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MicroPak2™ MotionMax™ MotionGrid® MTI® MTN® MVN® MVSaver® OptoHIT™ OPTOLOGIC®	OPTOPLANAR <sup>®</sup> → Power Supply WebDesigner <sup>TM</sup> PowerTrench <sup>®</sup> PowerXS <sup>TM</sup> Programmable Active Droop <sup>TM</sup> QFET <sup>®</sup> QS <sup>TM</sup> QGIt Series <sup>TM</sup> RapidConfigure <sup>TM</sup> → Saving our world, 1mW/W/kW at a time <sup>TM</sup> SignalWise <sup>TM</sup> SMART START <sup>TM</sup> Solutions for Your Success <sup>TM</sup> SPM <sup>®</sup> STEALTH <sup>TM</sup> SuperFET <sup>®</sup> SuperSOT <sup>TM</sup> -6 SuperSOT <sup>TM</sup> -8 SupreMOS <sup>®</sup> SyncFET <sup>TM</sup> SupreMOS <sup>®</sup> SyncLock <sup>TM</sup>	ESYSTEM で CECHERAL TinyBoost <sup>®</sup> TinyBuck <sup>®</sup> TinyLogic <sup>®</sup> TINYOPTOT <sup>M</sup> TinyPOwer <sup>TM</sup> TinyPOwer <sup>TM</sup> T
	Corporation, used under license by Fairchil	d Semiconductor.	
DISCLAIMER			

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. TO OBTAIN THE LATEST, MOST UP-TO-DATE DATASHEET AND PRODUCT INFORMATION, VISIT OUR WEBSITE AT <u>HTTP://WWW.FAIRCHILDSEMI.COM</u>. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used here in:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

#### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.Fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufactures of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed application, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handing and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address and warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

#### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed Full Production		Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete Not In Production		Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. 174



ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor has against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death ass

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

ON Semiconductor: FDMS6681Z