

U Cores (9077026002)



Part Number: 9077026002

77 U CORE

Explanation of Part Numbers: Digits 1&2 = product class, 3&4 = material grade.

The U core offers an economical core design with a nearly uniform cross-sectional area. In a power ferrite material they are frequently used in output chokes, power input filters and transformers for switched-mode power supplies and HF fluorescent ballasts.

□ For any U core requirement not listed in the catalog, please contact our customer service group for availability and pricing.

[Catalog Drawing](#)
[3D Model](#)

Weight indicated is per pair or set.

Weight: 15 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	25.4	±0.75	1	-
B	12.6	+0.25	0.501	-
C	6.35	/ >(0.250")	0.25	-
D	6.2	Min	0.245	Min
E	12.45	Min	0.49	Min




Figure 1

Chart Legend

•An I core, 9377024002, is available for these U cores. See I Core Section of our catalog.

$\Sigma l / A$: Core Constant, l_c : Effective Path Length, A_c : Effective Cross- Sectional Area, V_c :
Effective Core Volume

A_L : Inductance Factor 

Electrical Properties	
A_L (nH)	940 Min
A_e (cm ²)	0.4
$\Sigma l / A$ (cm ⁻¹)	17.6
l_c (cm)	7.1
V_c (cm ³)	2.85

□ A_L value is measured at 1kHz, < 10 gauss.

□ These U cores have the same minimum cross-sectional area as the listed effective cross-sectional area.

Fair- Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • ferrites@fair-rite.com • www.fair-rite.com