

POWER TRANSFORMER PC MOUNT: WORLD SERIES

VPP36-1560

Electrical Specifications (@25C)

- 1. Maximum Power: 56.0VA
- 2. Input: Series: 230VAC, 50/60Hz; Parallel: 115VAC, 50/60Hz
- 3. Output: Series¹: 36.0V CT@ 1.56A; Parallel²: 18.0V @ 3.12A
- 4. Voltage Regulation: 25% TYP @ full load to no load
- 5. Temperature Rise: 30C TYP (45C MAX allowed)
- 6. Insulation Resistance: 100MΩ
- 7. Hipot: 4000VAC between primary to secondary and windings to core.
- 8. Recommended Fuse3:

Series: Littelfuse p/n 313 2HXP, 2.0A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-2, 2.0A 250V, ¼ x 1 ¼ Parallel: Littelfuse p/n 313 4 HXP, 4A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-4, 4A 250V, ¼ x 1 ¼

Construction:

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

Safety:

Since the dual bobbin construction effectively reduces capacitance, electrostatic shielding is not required. World Series Transformers are designed and manufactured to meet the following agency approvals:

Units: In inches



Agency File:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose. UL: File E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3. CSA: File LR 221330. C22.2 NO. 66, General Purpose. TUV: File R72103639, EN 60950, (IEC950) information Technology Equipment.

Α.	Dimens	sions:

Н	W	D	А	В	С	ML	MD	MW
1.812	3.0	2.50	0.600	0.300	1.900	-	2.0	2.5

B. PIN DIM. : 0.045 SQ

C. WT Lbs. : 1.70

D. Mounting Holes: 0.180 dia. x 4

Connections⁴:

Input: Series – Pin 1 to Pin 6, Jumper Pin 4 to Pin 3

Parallel – Pin 1 to Pin 6, Jumper Pin 1 to Pin 4 and Pin 3 to Pin 6

Output: Series – Pin 7 to Pin 12, Jumper Pin 9 to Pin 10 Parallel – Pin 7 to Pin 12, Jumper Pin 7 to Pin 10 and Pin 9 to Pin 12

RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.


* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


³ Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.


⁴ Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757


460 Harley Knox Blvd. Perris, California 92571














Publish Date: June 3, 2019

¹ Non-Inherently limited. Class 3.

² Non-Inherently limited. Class 2 not wet, Class 3 wet.