

PART NAME	ECONOMIZER CABINET RACK (19" P.S., VENTED)	PART No.	ER-16602 thru ER-16626	REV. DATE	1-27-11
-----------	--	----------	------------------------	-----------	---------

NOTES:

- 1

PANEL MOUNTING RAILS TAPPED #10-32 ON E.I.A. UNIVERSAL SPACING AND ARE FULLY ADJUSTABLE.

2

MOUNTING HOLES PIERCED IN BASE FOR #RC-7758 CASTERS.

3

LOAD RATING: 1200 LBS. MAX.

☒

(2) SETS OF (10) HOODED LOUVERS CENTERED ON EACH SIDE.

☐

(2) SETS OF (15) HOODED LOUVERS CENTERED ON EACH SIDE.


☐

(4) SETS OF (10) HOODED LOUVERS ON EACH SIDE.

☐

(4) SETS OF (15) HOODED LOUVERS ON EACH SIDE.

MOUNTING PROVISIONS FOR OPTIONAL FAN.



TOP VIEW

22.000±0.062

2.625

17.937±0.093
18.312±0.062
19.125±0.031

A

B

2.625

FRONT VIEW

2.406

1.750

1.828

3.000

9.561 x 9.561
SQUARE CUTOUT

1.828

9.093

6.454

BOTTOM VIEW

OPTIONAL ACCESSORIES

PART NO.	PANEL SPACE A	B	C	D	E	F	PANEL MTG. RAILS PART NO.	ECONOGLAS DOORS PART NO.
ER-16602 ☒	42.000	47.312	18.500	17.000	—	38.562	PMR-9450	V-9763-L
ER-16603 ☐	52.500	57.812			—	49.062	PMR-9451	V-9764-L
ER-16604 ☐	61.250	66.562			27.531	57.812	PMR-9452	V-9765-L
ER-16605 ☐	70.000	75.312			31.906	66.562	PMR-9453	V-9766-L
ER-16606 ☐	78.750	84.062	18.500	17.000	36.281	75.312	PMR-9454	V-9767-L
ER-16612 ☐	42.000	47.312	25.500	24.000	—	38.562	PMR-9450	V-9763-L
ER-16613 ☐	52.500	57.812			—	49.062	PMR-9451	V-9764-L
ER-16614 ☐	61.250	66.562			27.531	57.812	PMR-9452	V-9765-L
ER-16615 ☐	70.000	75.312			31.906	66.562	PMR-9453	V-9766-L
ER-16616 ☐	78.750	84.062	25.500	24.000	36.281	75.312	PMR-9454	V-9767-L
ER-16622 ☐	42.000	47.312	30.750	29.250	—	38.562	PMR-9450	V-9763-L
ER-16623 ☐	52.500	57.812			—	49.062	PMR-9451	V-9764-L
ER-16624 ☐	61.250	66.562			27.531	57.812	PMR-9452	V-9765-L
ER-16625 ☐	70.000	75.312			31.906	66.562	PMR-9453	V-9766-L
ER-16626 ☐	78.750	84.062	30.750	29.250	36.281	75.312	PMR-9454	V-9767-L

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Bud Industries:

<u>ER-16602-S</u>	<u>ER-16602-RB</u>	<u>ER-16606-BT</u>	<u>ER-16606-RB</u>	<u>ER-16626-S</u>	<u>ER-16606-S</u>	<u>ER-16622-S</u>	<u>ER-16612-BT</u>
<u>ER-16612-RB</u>	<u>ER-16605-RB</u>	<u>ER-16605-BT</u>	<u>ER-16605-S</u>	<u>ER-16625-BT</u>	<u>ER-16625-RB</u>	<u>ER-16614-RB</u>	<u>ER-16614-BT</u>
<u>ER-16623-S</u>	<u>ER-16604-RB</u>	<u>ER-16602-BT</u>	<u>ER-16624-S</u>	<u>ER-16616-S</u>	<u>ER-16604-S</u>	<u>ER-16622-BT</u>	<u>ER-16622-RB</u>
<u>ER-16613-BT</u>	<u>ER-16613-RB</u>	<u>ER-16613-S</u>	<u>ER-16604-BT</u>	<u>ER-16603-BT</u>	<u>ER-16603-RB</u>	<u>ER-16612-S</u>	<u>ER-16626-RB</u>
<u>ER-16626-BT</u>	<u>ER-16623-BT</u>	<u>ER-16623-RB</u>	<u>ER-16616-RB</u>	<u>ER-16616-BT</u>	<u>ER-16625-S</u>	<u>ER-16614-S</u>	<u>ER-16615-S</u>
<u>ER-16615-BT</u>	<u>ER-16615-RB</u>	<u>ER-16624-RB</u>	<u>ER-16624-BT</u>	<u>ER-16603-S</u>	<u>16626S-RB</u>	<u>16626S-RB-PK</u>	