

|   |   |   |   |   |   |
|---|---|---|---|---|---|
|   |   |   |   |   |   |
| 3 | 4 | 5 | 6 | 7 | 8 |

\* When used with Kycon KMD and KMDG Series Sockets

| Tolerances                 |
|----------------------------|
| X.X $\pm$ 0.25             |
| X.XX $\pm$ 0.15            |
| Unless Stated<br>Otherwise |

**KMDAX-xP**  
x = No. of positions

RoHS Compliant



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Kycon:](#)

[KMDAX-6P](#) [KMDAX-4P](#) [KMDAX-8P](#) [KMDAX-5P](#) [KMDAX-7P](#) [KMDAX-3P](#)