Fuseholders



Bulgin's extensive range of fuseholders are designed to give the degree of protection demanded in today's sophisticated electronic equipment. Carrying world-wide safety approvals from UL, VDE, CSA and IMQ, all types are manufactured from high grade flame retardant nylon and polyester materials.

Designed primarily for 5×20 mm and 6.3×32 mm size fuses with protection against shock to categories PC1, PC2 and PC3. There's a choice of styles for in-line, PCB mounting and panel mounting (screw or snap fit) with terminal options for solder, 2.8mm, 4.8mm or 6.3mm tabs or PC spills. Dust and waterproof designs provide a front of panel seal to IP68 in both 5×20 mm and 6.3×32 mm size fuses.

Fuse carrier styles include captive drawer, screw cap - with screw driver release, bayonet cap - with screw driver release and screw cap - with finger release.

Panel Mounting IP68 Panel Mounting IP66 Panel Mounting PC Mounting Base Mounting 330-336 337 338 339-340 341 342-343





Fuseholders

Protection Category



Category PC1:

No integral protection against electric shock. If required, Designers/ Manufacturers must provide additional protection against electric shock on equipment.

Category PC2:

With integral protection against electric shock. Fuseholders shall have live parts inaccessible to IEC 60529 Standard Test Finger, when fully assembled, without fuse carrier or fuse in place and when fuse carrier, with fuse is being inserted or withdrawn.

Category PC3:

With integral protection against electric shock. Fuseholders shall have live parts inaccessible to IEC 60529 1mm dia. rigid test wire when fully assembled, without fuse carrier or fuse in place and when fuse carrier, with fuse, is being inserted or withdrawn.


Panel/PC Mounting Captive Carriers Touchproof, PC3



Snap Fit to Panel



- O Protection Category PC3
- Fuse Size 5 x 20mm Panel Sizes 1.0, 1.5, 2.0 and 3.0mm
- Captive Drawer 10A, 250V (16A, 250V UL)
- 2.8, 4.8 or 6.3 tabs








FX0430/PC

FX0430/63

- O Protection Category PC3
- Fuse Size 5 x 20mm
- Panel Sizes 1.0, 1.5, 2.0 and 3.0mm
- Captive Drawer
- 10A, 250V (16A, 250V UL)
- O PC spills



Specifications	FX0430/Termination	FX0430/PC
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	Captive Drawer	Captive Drawer
Terminations:	/28 (2.8mm solder), /48 (4.8mm tab), /63 (6.3mm tab)	/PC (PC spills)
Max. Rating:	10A, 250V (16A, 250V a.c. UL)	10A, 250V (16A, 250V a.c. UL)
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	$>10M\Omega$ @ 500V d.c.	>10MΩ @ 500V d.c.
A.C. Breakdown:	>2kV	>2kV
Contact Resistance:	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body/Drawer: Cap: Nut:	Nylon UL94V-0 rated	Nylon UL94V-0 rated
Contacts:	Contact tags: Brass, Tin Plated Fuse Clips: Phospher Bronze, Nickel Plated	Contact tags: Brass, Tin Plated Fuse Clips: Phospher Bronze, Nickel Plated
Approvals:	Plated A S	
Accessories:		
Note:		

Compliant Compliant

Panel Mounting and Snap Fit Touchproof, PC2








FX0357

FX0359

- O Protection Category PC2
- Fuse Size 5 x 20mm \bigcirc
- Bayonet Cap/Screwdriver Release
- 10A, 250V (16A, 250V UL)




Snap Fit to Panel



FX0367

FX0369

- \bigcirc **Protection Category PC2**
- Fuse Size 5 x 20mm
- Panel Sizes 1.0 & 1.5 and 2.0 & 3.0mm
- Bayonet Cap/Screwdriver Release
- 10A, 250V (16A, 250V UL)



Specifications FX0357, FX0359 FX0367/Panel, FX0369/Panel Fuse Size: 5 x 20mm 5 x 20mm /1 (1.0-1.5mm panel, black sleeve) Panel Size: /2 (2.0-3.0mm panel, grey sleeve) Fuse Carrier: Bayonet cap/Screwdriver release Bayonet cap/Screwdriver release

Terminations: Solder tags

10A, 250V (16A, 250V a.c. UL) Max. Rating:

2.5W (@ 23°C) Max. Power Dissipation:

Insulation Resistance: $>10^2 M\Omega$ @ 500V d.c.

A.C. Breakdown: 7kV @ 50Hz Contact Resistance: <10mΩ

-20°C to +85°C Operating Temp:

(ambient air temp + fuse temp rise)

Mouldings:

Polyester UL94V-0 rated Body: Nylon UL94V-0 rated Cap: Glass Filled Nylon UL94V-0 rated

Contacts: Brass, Silver Plated

*VDE APPROVALS PENDING Approvals:

Accessories: P.No. 11327 (See page 206)

RoHS Compliant Solder tags

10A, 250V (16A, 250V a.c. UL)

2.5W (@ 23°C)

 $>10^{2}M\Omega$ @ 500V d.c.

7kV @ 50Hz

<10mΩ

-20°C to +85°C

(ambient air temp + fuse temp rise)

Polyester UL94V-0 rated Nylon UL94V-0 rated

Brass, Silver Plated

*VDE APPROVALS PENDING

P.No. 11327 (See page 205)

Panel Mounting and Snap Fit Touchproof, PC2








FX0454,

FX0455

- Protection Category PC2
- O Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- Keyway Panel Cutout (FX0454)
- O D Panel Cutout (FX0455)
- O 10A, 250V (16A, 250V UL)




Panel Mount



FX0454/S

FX0455/S

- Protection Category PC2
- O Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- O High Profile Bezel
- Keyway Panel Cutout (FX0454/S)
- O D Panel Cutout (FX0455/S)
- 10A, 250V (16A, 250V UL)




Snap Fit to Panel



FX0458

- Protection Category PC2
- O Fuse Size 5 x 20mm
- O Panel Sizes 1.0 & 1.5 and
- O 2.0 & 3.0mm
- Screw Cap/Screwdriver Release
- O 10A, 250V (16A, 250V UL)



X0458/I I.0 & 2.0 & 2.0 &		

Compliant

Specifications	FX0454, FX0455	FX0454/S, FX0455/S	FX0458
Fuse Size:	5 x 20mm	5 x 20mm	5 x 20mm
Panel Size:			/1 (1.0-1.5mm panel, black sleeve) /2 (2.0-3.0mm panel, grey sleeve)
Fuse Carrier:	Screw cap/Screwdriver release	Screw cap/Screwdriver release	Screw cap/Screwdriver release
Terminations:	Solder tags	Solder tags	Solder tags
Max. Rating:	10A, 250V (16A, 250V a.c. UL)	10A, 250V (16A, 250V a.c. UL)	10A, 250V (16A, 250V a.c. UL)
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	$>10^2 M\Omega$ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.
A.C. Breakdown:	7kV @ 50Hz	7kV @ 50Hz	7kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: Nut:	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated	Brass, Silver Plated
Approvals:	*VDE APPROVALS PENDING	*VDE APPROVALS PENDING	91. ©
Accessories:	P.Nos. 11327, 12297 & 12298 (See page 206)	P.Nos. 11327, 12297 & 12298 (See page 206)	P.Nos. 11327 (See page 205)

Compliant

Panel Mounting Touchproof, PC2



Panel Mount




FX0415,

FX0416

O Protection Category PC2

Fuse Sizes:6.3 x 32mm (FX0415)6.3 x 25mm (FX0416)

- Screw Cap/Hand Release
- 13A, 250V (16A, 250V UL)




Panel Mount



Protection Category PC2

Fuse Sizes: 6.3 x 32mm (FX0415/S) 6.3 x 25mm (FX0416/S)

- Screw Cap/Screwdriver
- 13A, 250V (16A, 250V UL)



FX0415/S,	FX0416/S		(With Fuse Fitted)	Fixing Detail
Specifications	FX0415, FX0416	FX0415/S, FX0416/S		
Fuse Size:	FX0415 - 6.3 x 32mm FX0416 - 6.3 x 25mm	FX0415/S - 6.3 x 32mm FX0416/S - 6.3 x 25mm		
Fuse Carrier:	Screw cap/Hand release	Screw cap/Hand release		
Terminations:	4.8 series tabs	4.8 series tabs		
Max. Rating:	13A, 250V (16A, 250V UL)	13A, 250V (16A, 250V UL)		
Max. Power Dissipation:	4W (@ 23°C)	4W (@ 23°C)		
Insulation Resistance:	$>10^5 M\Omega$ @ 500V d.c.	$>10^5 M\Omega$ @ 500V d.c.		
A.C. Breakdown:	4kV @ 50Hz	4kV @ 50Hz		
Contact Resistance:	<5mΩ	<5mΩ		

Contact Resistance: $<5m\Omega$ $<5m\Omega$ Operating Temp: $-20^{\circ}\text{C to } +85^{\circ}\text{C}$ $-20^{\circ}\text{C to } +85^{\circ}\text{C}$ (ambient air temp + fuse temp rise) $-20^{\circ}\text{C to } +85^{\circ}\text{C}$

Mouldings:
Body: Glass Filled Nylon UL94V-0 rated
Cap: Nylon UL94V-0 rated
Nut: Polyester UL94V-0 rated

Contacts: Brass, Silver Plated

Approvals:

Accessories: P.No. 12932 (See page 205)

oHS Compliant

Glass Filled Nylon UL94V-0 rated Nylon UL94V-0 rated Polyester UL94V-0 rated

Brass, Silver Plated

Al

P.No. 12932 (See page 205)

Panel Mounting, PC2




Panel Mount



FX0354

- O Protection Category PC2
- \Diamond Low Profile Bezel
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- Keyway Panel Cutout
- 6.3A, 250V








FX0354/S

P.No. 11327 and 12298

(See page 205)

Compliant

- Protection Category PC2
- 0 High Profile Bezel
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- Keyway Panel Cutout
- 6.3A, 250V



	171000 170	
Specifications	FX0354	FX0354/S
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	Screw cap/Screwdriver release	Screw cap/Screwdriver release
Terminations:	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	$>10^2 M\Omega$ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.
A.C. Breakdown:	5kV @ 50Hz	5kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: Nut:	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated
Approvals:		

P.No. 11327 and 12298

(See page 205)

Compliant

Accessories:

RoHS

Fuseholders 6.3 x 32mm (11/4" x 1/4"), PC2





Key Features

- O 6.3 x 32mm fuses
- Screwdriver slot knob
- PC2 protection category
- 4.8, 6.3 and solder terminals
- Low profile bezel
- Snap in or threaded bushing mounting options

Approvals and specifications

(3)

10A 250V (max fuse rating*) T–55 to T+70 (ambient) Maximum dissipation wattage: 4W

16A UL 250V UL file E92075 CSA file LR44770

These products comply with safety category PC2. *Users should be aware of the de-rating factors published by specialist manufacturers of fuses.

Fuseholders with in-line termination have combination (4.8/6.3) terminals. It has not been possible to show both views here. Units with right angle terminals have user specified end terminals and combination mid-body terminals.





Fuseholders Panel Mounting, PC1




Panel Mount



FX0296/S

FX0296


- O Protection Category PC1
- Fuse Size 5 x 20mm
- Screw Cap/Hand Release
- 6.3A, 250V



Panel Mount



- FX0296/1
- O Protection Category PC1
- 000 Fuse Size 5 x 20mm
- Screw Cap/Hand Release
- 6.3A, 250V



Specifications	FX0296, FX0296/S	FX0296/1
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	FX0296 Screw cap/Hand release FX0296/S Screw cap/Screwdriver release	Screw cap/Hand release
Terminations:	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	$>10^5 M\Omega$ @ 500V d.c.	$>10^{5} M\Omega$ @ 500V d.c.
A.C. Breakdown:	2.5kV @ 50Hz	2.5kV @ 50Hz
Contact Resistance:	<5mΩ	$<5m\Omega$
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: Nut:	Glass Filled Nylon UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Glass Filled Nylon UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated
Contacts:	Brass, Silver or Tin Plated	Brass, Silver or Tin Plated
Accessories	P.No. 9820 (See page 205)	P.No. 9820 (See page 205)
RoHS	Compliant	Compliant


Panel Mounting Touchproof, Sealed to IP68, PC2



Panel Mount



- Panel sealed to IP68 Touchproof Category PC2
- Fuse Size 6.3 x 32mm
- Screw cap/Screwdriver/Hand Release
- 16A. 250V ac




FX0419

Panel Mount



FX0462


- Panel sealed to IP68
- Touchproof Category PC2
- Fuse Size 5 x 20mm
- Screw cap/Screwdriver/Hand Release
- 10A. 250V ac



Panel Mount



- Panel sealed to IP68 Touchproof Category PC2
- Fuse Size 5 x 20mm
- High Profile Bezel
- Screw cap/Screwdriver/Hand Release
- 10A. 250V ac



Specifications	FX0419	FX0462	FX0463
Fuse Size:	6.3 x 32mm	5.0 x 20mm	5.0 x 20mm
Fuse Carrier:	Screw cap/Screwdriver/Hand release	Screw cap/Screwdriver/Hand release	Screw cap/Screwdriver/Hand release
Terminations:	6.3 series tabs	Solder tags	Solder tags
Max. Rating:	16A, 250V ac	10A, 250V ac	10A, 250V ac
Max. Power Dissipation:	2.5W (@ 23°C)	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	$>10^6 M\Omega$ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.	>10 ² MΩ @ 500V d.c.
A.C. Breakdown:	>2kV @ 50Hz	>7kV @ 50Hz	>7kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: Nut:	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Glass Filled Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated	Brass, Silver Plated
Tightening Torque: Cap: Panel Nut:	0.5 - 0.6Nm (4.43-5.3lbf.in.) 0.5Nm (4.4lbf.in.)	0.4 - 0.6Nm (3.54-5.3lbf.in.) 0.5Nm (4.4lbf.in.)	0.4 - 0.6Nm (3.54-5.3lbf.in.) 0.5Nm (4.4lbf.in.)
Sealing:	IP68 to EN60529:1992+A2:2013 (10m for 2weeks)	IP68 to EN60529:1992+A2:2013 (10m for 2weeks)	IP68 to EN60529:1992+A2:2013 (10m for 2weeks)
Accessories:		P.nos. 11327 (see page 205)	P.nos. 11327 (see page 205)
Approvals:	*VDE APPROVALS PENDING	*VDE APPROVALS PENDING	*VDE APPROVALS PENDING
RoHS	Compliant	Compliant	Compliant


Panel Mounting Touchproof, Sealed to IP66, PC1



High Profile Panel Mount




- O Sealed to IP66
- Protection Category PC1
- Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- O 6.3A, 250V



High Profile Panel Mount



- Sealed to IP66
- **Protection Category PC1**
- O Fuse Size 5 x 20mm
- Screw Cap/Hand Release
- Large Cap for Easy Grip6.3A, 250V



 \/	$\overline{}$	0	\sim	r
FX	U	ß	Ю	t

Specifications	FX0345, FX0345/A	FX0365, FX0365/A
Fuse Size:	5 x 20mm	5 x 20mm
Fuse Carrier:	Screw cap/Screwdriver release	Screw cap/Screwdriver release
Terminations:	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V
Max. Power Dissipation:	4W (@ 23°C)	4W (@ 23°C)
Insulation Resistance:	$>10^3 M\Omega$ @ 500V d.c.	>10 ⁹ MΩ @ 500V d.c.
A.C. Breakdown:	>3.5kV @ 50Hz	>3.5kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body & Cap: Spacer: Insulating Sleeve:	Glass Filled Nylon UL94V-0 rated Glass Filled Nylon UL94HB rated Nylon UL94V-0 rated	Glass Filled Nylon UL94V-0 rated Glass Filled Nylon UL94HB rated Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated
Sealing:	Protection Classification IP66 to EN60529:1992+A2:2013 Retains sealing integrity with cap removed since they are both panel and barrier sealed	
Variants:	/A Silicone 'O' ring, Op. Temp55°C to +85°C Compliant	/A Silicone 'O' ring, Op. Temp. –55°C to +85°C Compliant

PC Mounting PC1, PC2 and PC3



PC Horizontal Mount



- FX0461
- O Protection Category PC3
- O Fuse Size 5 x 20mm
- Screw Cap/Screwdriver Release
- Captive Fuse Carrier
- 0 PC Spills
- 10A, 250V (16A, 250V UL)
- 4 HOLES Ø1.3 +0.1 01.3 +0.0 P.C.B. Fixing Detail






FX0457

FX0456

- **Protection Category PC2**
- Fuse Sizes 5 x 20mm
- Bayonet Cap/Screwdriver Release
- O 10A, 250V




PC Horizontal Mount



FX0330

- O Protection Category PC1
- O Fuse Size 5 x 20mm
- ŏ O O
- Two or Three PC Spills Screw Cap/Hand Release
- 6.3A, 250V



Specifications	FX0461	FX0456 FX0457	FX0330 FX0342
Fuse Size:	5 x 20mm	5 x 20mm	5 x 20mm
Fuse Carrier:	Screw cap/Screwdriver release	Bayonet cap/Screwdriver release	Screw cap/Hand release
Terminations:	PC Spills	PC Spills	FX0330 - 3 PC Spills
Max. Rating:	10A, 250V (16A, 250V a.c. UL)	10A, 250V	FX0342 - 2 PC Spills 6.3A, 250V
Max. Power Dissipation:	1.6W (@ 23°C)	2.5W (@ 23°C)	2.5W (@ 23°C)
Insulation Resistance:	>10MΩ @ 500V d.c.	$>10^2 M\Omega$ @ 500V d.c.	>10⁴MΩ @ 500V d.c.
A.C. Breakdown:	>2kV	4kV @ 50Hz	6kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<5mΩ
Operating Temp:	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)	-20°C to +85°C (ambient air temp + fuse temp rise)
Mouldings: Body: Cap: End Bung:	Polyester UL94V-0 rated Nylon UL94V-0 rated	Polyester UL94V-0 rated Nylon UL94V-0 rated Polyester UL94V-0 rated	Glass Filled Nylon UL94V-0 rated Nylon UL94V-0 rated
Contacts:	Brass, Silver Plated	Brass, Silver Plated	Brass, Tin Plated
Approvals:	FL @ @	*VDE APPROVALS PENDING	
RoHS	Compliant	Compliant	Compliant

PC and Base Mounting, PC1








FX0321

- O Protection Category PC1
- O Fuse Size 5 x 20mm
- PC Spills○ 6.3A, 250V




Base Mount



FX0267


- Protection Category PC1Fuse Size 5 x 20mm
- Solder Tags
- 6.3A, 250V



Base Mount



- O Protection Category PC1
- Fuse Size 5 x 20mm
- Solder Tags
- 6.3A, 250V




Specifications	FX0321	FX0267	FX0360
Fuse Size:	5 x 20mm	5 x 20mm	5 x 20mm
Terminations:	PC Spills	Solder tags	Solder tags
Max. Rating:	6.3A, 250V	6.3A, 250V	6.3A, 250V
Insulation Resistance:	$>10^5 M\Omega$ @ 500V d.c.	$>10^5$ M Ω @ 500V d.c.	$>10^4$ M Ω @ 500V d.c.
A.C. Breakdown:	7kV @ 50Hz (Clip to clip)	1.5kV @ 50Hz	2kV @ 50Hz
Contact Resistance:	<10mΩ	<10mΩ	<10mΩ
Operating Temp: (ambient air temp + fuse temp rise)	–20°C to +85°C	-20°C to +85°C	-20°C to +85°C
Base Material:	Glass Filled Nylon UL94V-0 rated	Glass Filled Nylon UL94V-0 rated	Glass Filled Nylon UL94HB rated
Contacts:	Phospher Bronze, Tin Plated	Phospher Bronze, Tin Plated	Phospher Bronze, Tin Plated
Accessories:	P.No. 12760 (See page 205)	P.No. 12760 (See page 205)	
RoHS	Compliant	Compliant	Compliant

Base Mounting, PC1





- O Protection Category PC1
- O Fuse Sizes: 6.3 x 32mm (FX0326) 6.3 x 25mm (FX0331)
- Solder Tags
 13A, 250V







- Protection Category PC1Fuse Size 6.3 x 32mm
- Solder Tags
- O 5A, 250V

Specifications	FX0326, FX0331	FX0327
Fuse Size:	FX0326 - 6.3 x 32mm FX0331 - 6.3 x 25mm	6.3 x 32mm
Terminations:	6.3 series tabs	Solder tags
Max. Rating:	13A, 250V	5A, 250V
Insulation Resistance:	$>10^4$ M Ω @ 500V d.c.	>10 ⁵ MΩ @ 500V d.c.
A.C. Breakdown:	5kV @ 50Hz	5kV @ 50Hz
Contact Resistance:	<5mΩ	<10mΩ
Operating Temp: (ambient air temp + fuse temp rise)	–20°C to +85°C	-20°C to +85°C
Base Material:	Glass Filled Polyester UL94V-0 rated	Glass Filled Polyester UL94V-0 rated
Contacts:	Clips: Phospher Bronze, Tin Plated Tabs: Brass, Tin Plated	Phospher Bronze, Tin Plated
RoHS	Compliant	Compliant

In-Line PC1 and In-Line Sealed to IP66, PC1








FX0180, FX0280,

FX0380

- O Protection Category PC1
- Fuse Sizes 5 x 20mm, 6.3 x 25mm and 6.3 x 32mm
- Screw Terminal (Solder to order)
- 10A, 50V (250V Inaccessible)
- UL Approved (Black Only)
- O Clear or black



In-line



FX0185,

FX0285,

FX0385

Sealed to IP66

- \bigcirc **Protection Category PC1**
- O Fuse Sizes 5 x 20mm, 6.3 x 25mm and 6.3 x 32mm
- Screw Terminal (Solder to order)
- 10A, 50V (250V Inaccessible) 0
- UL Approved (Black Only)
- Clear or black

15.49+/-0.1	A	
Stage 1— Stage 2— Stage 3—	List No FXO185 FXO285 FXO385	DIM A 91.0 85.2 78.7 +/-0.9

Body - Black: Grommet: O Ring: Contacts:

Terminals: Brass, Nickel Plated Grub Screw: Stainless Steel

Approvals: (Black version only)

Clear - no suffix, /BK - Black RoHS Compliant

Nitrile

Brass, Nickel Plated Stainless Steel

(Black version only)

Clear - no suffix, /BK - Black

Specifications	FX0180/colour, FX0280.colour, FX0380/Colour	FX0185/Colour, FX0285/colour, FX0385/Colour
Fuse Size:	5 x 20mm FX0380 6.3 x 25mm FX0280 6.3 x 32mm FX0180	5 x 20mm FX0385 6.3 x 25mm FX0285 6.3 x 32mm FX0185
Cable Acceptance:	1mm² conductor (max.)	1mm2 conductor (max.) 1mm to 2.64mm overall diameter Stepped grommet: Stage 1: 1.00mm to 1.40mm Stage 2: 1.50mm to 1.90mm Stage 3: 2.0mm to 2.64mm
Terminations:	Screw terminal (solder to order)	Screw Terminal (solder to order)
Max. Rating:	10A, 50V (250V where inaccessible inside equipment)	10A, 50V (250V where inaccessible inside equipment)
Insulation Resistance: High Voltage Proof Test: Contact Resistance:	$>10^5$ M Ω @ 500V d.c. 2kV (50Hz for 1 minute) $<10m\Omega$	$>10^5$ M Ω @ 500V d.c. 2kV (50Hz for 1 minute) $<10m\Omega$
Operating Temp: (ambient air temp + fuse temp rise)	-20°C to +90°C	-20°C to +70°C
Sealing:		Protection Classification IP66 EN60529: 1992+A2:2013
Screw Tightening Torque	0.226Nm (2lb/in)	0.226Nm (2lb/in)
Mouldings: Body - Clear: Body - Black:	Polybutene UL94HB rated Nylon 6 UL94V-0 rated	Polybutene UL94HB rated Nylon 6 UL94V-0 rated

Accessories




Insualtion Boots



PNo. 9820 PNo. 11327 PNo. 12932

- Provide Insulation against Shock on Rear of Fuseholder
- PVC
- UL94V-0 rated flame retardant material




Insualtion Cover



PNo. 12760

- Provide Insulation from Live Parts on Fuseholder
- \bigcirc Clear
- Polycarbonate




Adaptor



PNo. 12297

- Adaptor to Convert Fixing Holes
- Maintains Anti-Rotation
- Glass Filled Nylon



Accessories	For Use With	:

P.No. 9820 (Boot) FX0296, FX0296/1, FX0296/S

FX0354, FX0354/S, FX0357, FX0359, FX0454, FX0454/S, FX0455, FX0455/S, FX0460, FX0458, P.No. 11327 (Boot)

FX0367, FX0369, FX0462, FX0463

FX0415, FX0415/S, FX0416, FX0416/S P.No. 12932 (Boot)

FX0267, FX0321 P.No. 12760 (Cover)

Max. Working Voltage: 250V a.c. Flash Tested to: 2kV a.c.

P.Nos. 9820, 11327, 12932: PVC - UL94V-0 P.No. 12760: Polycarbonate Material:

Adapts 'D' fixing to anti-rotation Key Fixing FX0455, FX0455/S P.No. 12297

(Adaptor Washer)

Glass Filled Nylon Material:

RoHS Compliant

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Bulgin:

FX0430/63 FX0180 FX0180/BK FX0185 FX0267 FX0321 FX0326 FX0330 FX0345 FX0357 FX0359 FX0360

FX0365 FX0367/1 FX0367/2 FX0369/1 FX0369/2 FX0380 FX0385 FX0415 FX0415/S FX0419 FX0454

FX0454/S FX0455 FX0455/S FX0456 FX0457 FX0458/1 FX0458/2 FX0462 FX0463 FX0296 FX0354 FX0460

FX0461 FX0027/PC FX0354/S