



MK03 Series Reed Sensors



- Features: Cylindrical Reed Sensor, Choice of Cable Termination & Lengths available, Various Case Sizes
- Applications: Door & Window Contacts, With Magnetic Floats for Water Level Detection, Position Sensing
- Markets: Appliance, Industrial, Security & Others

Part Description: **M K 0 3 - 0 X 0 0 X - 0 0 0 X**



Contact QTY	Contact Form	Switch Model	Magnetic Sensitivity	Cable Length (mm)	Termination
1	A, B, C	66, 75, 90	B, C, D, E	200, 300, 500, 1,000, 1,500, 2,000, 3,000, 5,000	W

Customer Options		Switch Model			Unit
Contact Data		66	75	90	
Rated Power (max.) Any DC combination of V&A not to exceed their individual max.'s		10	10	10	W
Switching Voltage (max.) DC or peak AC		200	500	175	V
Switching Current (max.) DC or peak AC		0.5	0.5	0.5	A
Carry Current (max.) DC or peak AC		1.0	1.0	1.0	A
Contact Resistance (max.) @ 0.5V & 50mA		150	200	150	mOhm
Breakdown Voltage (min.) According to EN60255-5		0.25	1.5	0.2	kVDC
Operating Time (max.) Incl. Bounce; Measured with w/ Nominal Voltage		0.7	0.5	0.7	ms
Release Time (max.) Measured with no Coil Excitation		0.05	0.1	1.5	ms
Insulation Resistance (typ.) Rh<45%, 100V Test Voltage		10 ¹⁰	10 ¹⁰	10 ⁹	Ohm
Capacitance (typ.) @ 10kHz across open Switch		0.3	0.4	1.5	pF

Series Datasheet – MK03 Reed Sensors

www.standexmeder.com

Housing and Cable Specifications	
Housing Material	PBT Glass Fiber Reinforced
Case Color	White
Sealing Compound	Polyurethan
Cable Typ	Flat Cable
Cable Material	PVC
Cross Section (mm ²)	2 x 0.14


Environmental Data		Unit
Shock Resistance (max.) 1/2 sine wave duration 11ms	50	g
Vibration Resistance (max.)	20	g
Operating Temperature Cable not moved	-30 to 70	°C
Operating Temperature Cable moved	-5 to 70	°C
Storage Temperature	-30 to 70	°C

Glossary Contact Form		
Form A	NO = Normally Open Contacts SPST = Single Pole Single Throw	
Form B	NC = Normally Closed Contacts SPST = Single Pole Single Throw	
Form C	Changeover SPDT = Single Pole Double Throw	

Glossary Magnetic Sensitivity							
Sens.	A	B	C	D	E	F	G
AT	05-10	10-15	15-20	20-25	25-30	30-35	35-40



Handling & Assembly Instructions	
➤	Max torque on housing is 1Nm
➤	Cable bending-radius is diameter x 15
➤	Min. bending distance to housing is 5mm
➤	Drag mark out of the mounting area forbidden
➤	Decrease switching distance by mounting on iron
➤	Do not use magnetically inductive screws
➤	Series resistor recommended for > 5m cable length



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Standex Electronics](#):

[MK03-1A66B-500W](#) [MK03-1B-90C-1000W](#) [MK03-1A66B-100W](#) [MK03-1B90B-500W](#)