

POWER TRANSFORMER CHASSIS MOUNT: Autotransformer

N-2X

Electrical Specifications (@25°C)

1. Maximum Power: 100 VA

2. Input Voltage: 230 V, 50 / 60 Hz
3. Output Voltage 115V, ± 5%
4. Full Secondary Load 0.87 Amps RMS

5. Temperature Rise: 60C TYP (85C MAX allowed)

from 25° C, Ambient

Construction:

Single winding on a double wall, nylon bobbin. This chassis mount design comes in a channel frame with .187" diameter holes in the mounting ears. Three leads exit the transformer, the black lead is the tap.

Description:

Secondary coil is a fraction of the entire winding for voltage step-down. This causes part of the power to be transferred conductively through the windings, rather than all of the power being transferred by induction.

Safety:

These units are designed with 1500V isolation between the winding and the core. Materials and construction are rated for Class B insulation system. UL: File E50476, UL 1446, Electrical Insulation System



E50476


A. Dimensions: Unit: In inches

Н	W	D	MW
2.70 Max	4.0 Max	2.05 Max	3.562 ± 0.030

Weight: 2.1 lbs

Connections: 7 ± 1" leads, 0.250 ± 0.062" Stripped & Tin

Schematic:




For 230V input: Wht to Red For 115 output: Wht to BLK


RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571







Publish Date: September 6, 2016

^{*} Upon printing,this document is considered"uncontrolled".Please contact Triad Magnetics' website for the most current version.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Triad Magnetics:

<u>N-2X</u>