

40×40×28 mm

San Ace 40 9GV type



General Specifications

- Material Frame: Plastic (Flammability: UL 94V-0), Impeller: Plastic (Flammability: UL 94V-0)
- Expected life See the table below. (L10 life: 90% survival rate for continuous operation in free air at 60°C, rated voltage)
- Motor protection function Locked rotor burnout protection, Reverse polarity protection
For details, please refer to p. 529.
- Dielectric strength 50/60 Hz, 500 VAC, for 1 minute (between lead wire conductors and frame)
- Insulation resistance 10 MΩ or more with a 500 VDC megger (between lead wire conductors and frame)
- Sound pressure level (SPL) At 1 m away from the air inlet
- Storage temperature -20 to +70°C (Non-condensing)
- Lead wire ⊕Red ⊖Black or Blue (Sensor) Yellow
- Mass 50 g

Specifications

The models listed below **have ribs and pulse sensors**. For models without ribs, append "1" to the end of model numbers.


Model no.	Rated voltage [V]	Operating voltage range [V]	Rated current [A]	Rated input [W]	Rated speed [min ⁻¹]	Max. airflow [m ³ /min] [CFM]	Max. static pressure [Pa] [inchH ₂ O]	SPL [dB (A)]	Operating temperature [°C]	Expected life [h]
9GV0412K301	12	10.8 to 12.6	0.84	10.08	16500	0.76 26.8	415 1.668	58	-20 to +60	40000/60°C
9GV0412J301		7 to 13.2	0.6	7.2	14700	0.68 24.0	330 1.325	55		
9GV0412G301			0.47	5.64	13000	0.6 21.1	260 1.044	52		
9GV0412H301			0.31	3.72	11600	0.53 18.7	207 0.831	49		
9GV0412C301			0.15	1.8	8300	0.37 13.1	100 0.402	41	-20 to +70	

Other sensor specifications are available as options. Refer to the index (p. 554).

Airflow - Static Pressure Characteristics


9GV0412K301 With pulse sensor

Operating voltage range




9GV0412J301 With pulse sensor

Operating voltage range



9GV0412G301 With pulse sensor

Operating voltage range



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Sanyo Denki:

[9GV0412J3011](#) [9GV0412K3011](#) [9GV0412P3J03](#) [9GV0412P3K03](#) [9GV0412J301](#) [9GV0412K301](#) [9GV0412G301](#)
[9GV0412G3011](#) [9GV0412K3D01](#) [9GV0412J3D011](#) [9GV0412P3G031](#) [9GV0412J302](#) [9GV0412G3021](#)
[9GV0412K3021](#) [9GV0412P3H01](#) [9GV0412G3D011](#) [9GV0412J3D01](#) [9GV0412P3G03](#) [9GV0412G3D01](#)
[9GV0412G302](#) [9GV0412J3021](#) [9GV0412K302](#) [9GV0412J3013](#) [9GV0412H301](#) [9GV0412P3K031](#)