
Axial Lead & Cartridge Fuses PICO® > Very Fast-Acting Fuse > 275 Series

275 Series, PICO® Very Fast-Acting Fuse





Description

The PICO® Very Fast-Acting Fuse is designed to meet an extensive array of performance characteristics in a space-saving subminiature package.

Features

- Very fast-acting
- Small size
- High current rating (20A- 30A)

Electrical Characteristics

- RoHS compliant
- Wide operating temperature range
- Low temperature rerating

Agency Approvals

| Agency | Agency File Number | Ampere Range |
|-----------------|--------------------|--------------|
| c FL °us | E10480 | 20A - 30A |

Applications

- Power supply
- Networking equipment
- PC server
- Storage system

Additional Information







% o

| % of Ampere Rating | Ampere Rating | Opening Time |
|-----------------------|---------------|--------------------------|
| 100% | 20A - 30A | 4 Hours, Min. |
| 200% | 20A - 30A | 10 Seconds, Max . |

Electrical Characteristics


| Ampere Rating (A) | Amp Code | Ordering Number | Max Voltage Rating (V) | Interrupting Rating | Nominal Cold Resistance (Ohms) | Nominal Melting I²t (A² sec) | Agency Approvals |
|-------------------------|----------|--------------------|---------------------------------|--------------------------|--------------------------------------|------------------------------------|---------------------|
| 20.0 | 020. | 0275020. | 32 | 300A@32VDC 100A@32VAC | 0.0033 | 203 | х |
| 25.0 | 025. | 0275025. | 32 | | 0.0024 | 288 | х |
| 30.0 | 030. | 0275030. | 32 | | 0.0020 | 355 | х |

Axial Lead & Cartridge Fuses

PICO® > Very Fast-Acting Fuse > 275 Series



Temperature Re-rating Curve



Note:

Rerating depicted in this curve is in addition to the standard derating of 25% for continuous operation.

Soldering Parameters

Recommended Process Parameters:

| Wave Parameter | Lead-Free Recommendation |
|---|-----------------------------------|
| Preheat: (Depends on Flux Activation Temperature) | (Typical Industry Recommendation) |
| Temperature Minimum: | 100°C |
| Temperature Maximum: | 150°C |
| Preheat Time: | 60-180 seconds |
| Solder Pot Temperature: | 260°C Maximum |
| Solder DwellTime: | 2-5 seconds |


Recommended Hand-Solder Parameters:

Solder Iron Temperature: 350°C +/- 5°C Heating Time: 5 seconds max.

Convection Reflow process.

Note: These devices are not recommended for IR or

Average Time Current Curves



Axial Lead & Cartridge Fuses PICO® > Very Fast-Acting Fuse > 275 Series


Product Characteristics

| Materials | Transparent Polyvinylidene Fluoride sleeve covered body, pure tin plated copper wire leads | | |
|-----------------|--|--|--|
| Solderability | MIL-STD-202, Method 208 | | |
| Lead Pull Force | MIL-STD-202, Method 211, Test Condition A (will withstand a 5lbs. axial pull test) | | |

| Operating Temperature | -60°C to +125°C (Consider re-rating) |
|-----------------------|---|
| Shock | MIL-STD-202, Method 213, Test Condition I (100 G's peak for 6 milliseconds) and per method 2028 (78G's peak for 11 milliseconds) |
| Vibration | MIL-STD-202, Method 201 (10–55 Hz); Method 204, Test Condition D (Vibrations of 10-2000 cps at 20 G's) |
| Moisture Resistance | MIL-STD-202, Method 106 |


Dimensions

275 000 Series



| Amperage | Dimensions in mm (inches) | | | |
|----------|---------------------------|-------------------|-----------------|------------------|
| | Α | В | C | D |
| 20 - 30 | 7.87 (.31") | 27.78 (1.094") | 3.38 (.133") | 1.016 (.040") |

Part Numbering System



Only RoHS parts are available for 275 Series

Packaging

| Packaging Option | Packaging Specification | Quantity & Packaging Code | |
|-----------------------------------|-------------------------|--|--|
| T1: 52.4mm (2.062") Tape and Reel | EIA 296 | Please refer to available quantities above in "Part Numbering System" | |

The default lead length for loose pack is T1.

Disclaimer Notice - Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at www.littelfuse.com/disclaimer-electronics.