



preci-dip

WWW.PRECIDIP.COM TEL +41 32 421 04 00 SALES@PRECIDIP.COM

SPRING-LOADED CONNECTORS

2.54 mm GRID / SINGLE ROW / DOUBLE ROW / SOLDER TAIL


Low resistance modular connectors with spring-loaded contacts (SLC), solder tail. Contacts with improved, shaped piston design.

TECHNICAL SPECIFICATIONS (FOR GENERAL SPECS, SEE PAGE 31)

INSULATOR	Black glass filled polyester PCT-GF30-FR	
FLAMMABILITY	UL 94V-0	
PISTON AND BARREL	Brass CuZn36Pb3 (C36000)	
SPRING	Music wire DIN 17223, gold plated	
MAX. STROKE	1.4 mm	
FORCES	0.25 N initial	0.85 N at 1/2 stroke
MECHANICAL LIFE	50'000 cycles	
OPERATING CURRENT	Max. 3.5 A	
CONTACT RESISTANCE	10 mΩ (static measurement, halfway position)	

ORDERING INFORMATION ROHS COMPLIANT PARTS

PLATING CODE	BARREL	PISTON
S1	0.25 μm gold	0.5 μm gold
SS	0.5 μm gold	0.5 μm gold




See page 178 for plating specs.

NNN number of poles: Replace **NNN** with the requested number of poles, e.g. 813-S1-**NNN**-10-014101 for a double row version with 16 pins becomes 813-S1-**016**-10-014101.

811-S1-**NNN**-10-**XXX**101

Straight SLC connector, low profile, solder tail, single row


AVAILABILITY FROM 2 to 64 contacts
(standard number of contacts: 64)



813-S1-**NNN**-10-**XXX**101

Straight SLC connector, low profile, solder tail, double row


AVAILABILITY FROM 4 to 72 contacts
(standard number of contacts: 72)



813-SS-**NNN**-10-474101

Straight SLC connector, solder tail, double row

AVAILABILITY FROM 4 to 64 contacts
(standard number of contacts: 64)



AVAILABLE CONNECTOR HEIGHTS

INITIAL HEIGHT A (mm)	PLASTIC BODY HEIGHT B (mm)	XXX CODE
6	4	014
6.5	4	015
7	4	016
7.5	4	017

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Preci-dip:

[813-S1-022-10-014101](#) [813-S1-018-10-014101](#) [813-S1-016-10-014101](#) [813-S1-014-10-014101](#) [813-S1-012-10-014101](#) [813-S1-010-10-014101](#) [813-S1-066-10-017101](#) [813-S1-064-10-017101](#) [813-S1-014-10-017101](#) [813-S1-038-10-017101](#) [813-S1-058-10-017101](#) [813-S1-072-10-017101](#) [813-S1-070-10-017101](#) [813-S1-068-10-017101](#) [813-S1-026-10-017101](#) [813-S1-024-10-017101](#) [813-S1-022-10-017101](#) [813-S1-020-10-017101](#) [813-S1-018-10-017101](#) [813-S1-016-10-017101](#) [813-S1-060-10-017101](#) [813-S1-036-10-017101](#) [813-S1-062-10-017101](#) [813-S1-032-10-017101](#) [813-S1-030-10-017101](#) [813-S1-028-10-017101](#) [813-S1-050-10-017101](#) [813-S1-048-10-017101](#) [813-S1-046-10-017101](#) [813-S1-044-10-017101](#) [813-S1-042-10-017101](#) [813-S1-040-10-017101](#) [813-S1-030-10-015101](#) [813-S1-034-10-017101](#) [813-S1-056-10-017101](#) [813-S1-054-10-017101](#) [813-S1-052-10-017101](#) [813-S1-016-10-015101](#) [813-S1-014-10-015101](#) [813-S1-012-10-015101](#) [813-S1-010-10-015101](#) [813-S1-008-10-015101](#) [813-S1-006-10-015101](#) [813-S1-028-10-015101](#) [813-S1-052-10-015101](#) [813-S1-024-10-015101](#) [813-S1-022-10-015101](#) [813-S1-020-10-015101](#) [813-S1-018-10-015101](#) [813-S1-040-10-015101](#) [813-S1-038-10-015101](#) [813-S1-036-10-015101](#) [813-S1-034-10-015101](#) [813-S1-032-10-015101](#) [813-S1-070-10-014101](#) [813-S1-026-10-015101](#) [813-S1-012-10-017101](#) [813-S1-048-10-015101](#) [813-S1-046-10-015101](#) [813-S1-044-10-015101](#) [813-S1-042-10-015101](#) [813-S1-034-10-014101](#) [813-S1-032-10-014101](#) [813-S1-030-10-014101](#) [813-S1-028-10-014101](#) [813-S1-026-10-014101](#) [813-S1-050-10-014101](#) [813-S1-004-10-015101](#) [813-S1-044-10-014101](#) [813-S1-042-10-014101](#) [813-S1-040-10-014101](#) [813-S1-038-10-014101](#) [813-S1-036-10-014101](#) [813-S1-058-10-014101](#) [813-S1-056-10-014101](#) [813-S1-054-10-014101](#) [813-S1-052-10-014101](#) [813-S1-072-10-014101](#) [813-S1-048-10-014101](#) [813-S1-054-10-015101](#) [813-S1-068-10-014101](#) [813-S1-066-10-014101](#) [813-S1-064-10-014101](#) [813-S1-062-10-014101](#) [813-S1-060-10-014101](#) [813-S1-040-10-016101](#) [813-S1-038-10-016101](#) [813-S1-036-10-016101](#) [813-S1-050-10-015101](#) [813-S1-058-10-016101](#) [813-S1-046-10-014101](#) [813-S1-052-10-016101](#) [813-S1-050-10-016101](#) [813-S1-048-10-016101](#) [813-S1-046-10-016101](#) [813-S1-044-10-016101](#) [813-S1-042-10-016101](#) [813-S1-064-10-016101](#) [813-S1-062-10-016101](#) [813-S1-060-10-016101](#)