

# INTERCONNECTS

## SERIES 850, 851, 852, 853 • .050" GRID HEADERS AND SOCKETS • SINGLE AND DOUBLE ROW STRIPS



**FIG. 1**



**FIG. 2**



**FIG. 3**



**FIG. 4**



**FIG. 5**

- Series 850, 851, 852, 853 single and double row interconnects have .050" pin spacing and permit board stacking as low as .248"
- Pin headers have .016" dia. pins (MM #4006-0) See page 208 for details
- MM #0467 and MM #4890 receptacles use Hi-Rel, 3-finger BeCu #11 contact rated at 3 amps. (#11 contact accepts pin diameters from .015"-.020"). See pages 158 and 160 for details
- Insulators are high temperature thermoplastic, suitable for all soldering operations



### ORDERING INFORMATION

<b>FIG. 1</b>	<b>Series 850...001</b>	<b>Single Row .087" Profile Pin Header</b>					
		850-XX-0__-10-001000 Specify number of pins    01-50					
<b>FIG. 2</b>	<b>Series 852...001</b>	<b>Double Row .083" Profile Pin Header</b>					
		852-XX-__-10-001000 Specify number of pins    004-100					
<b>SPECIFY PLATING CODE XX=</b>		10	90	40			
Pin Plating		10 μ" Au	200 μ" Sn/Pb	200 μ" Sn			
<b>FIG. 3</b>	<b>Series 851...001</b>	<b>Single Row .161" Profile Socket</b>					
		851-XX-0__-10-001000 Specify number of pins    01-50					
<b>FIG. 4</b>	<b>Series 853...001</b>	<b>Double Row .161" Profile Socket</b>					
		853-XX-__-10-001000 Specify number of pins    004-100					
<b>FIG. 5</b>	<b>Series 851...002</b>	<b>Single Row .185" Profile Socket</b>					
		851-XX-0__-10-002000 Specify number of pins    01-77					
<b>SPECIFY PLATING CODE XX=</b>		91	93	99	41	43	47
Sleeve (Pin)		200 μ" Sn/Pb	200 μ" Sn/Pb	200 μ" Sn/Pb	200 μ" Sn	200 μ" Sn	200 μ" Sn
Contact (Clip)		10 μ" Au	30 μ" Au	100 μ" Sn/Pb	10 μ" Au	30 μ" Au	Au Flash



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Mill-Max:

[853-99-100-10-001000](#) [853-99-050-10-001000](#) [853-93-050-10-001000](#) [852-90-100-10-001000](#) [852-90-050-10-001000](#) [851-99-077-10-002000](#) [851-99-050-10-001000](#) [851-99-025-10-001000](#) [851-93-077-10-002000](#) [851-93-025-10-001000](#) [850-90-050-10-001000](#) [850-90-025-10-001000](#) [850-10-050-10-001000](#) [850-10-006-10-001000](#) [850-10-007-10-001000](#) [851-93-013-10-001000](#) [853-99-016-10-001000](#) [853-43-100-10-001000](#) [851-93-050-10-001000](#) [851-93-004-10-002000](#) [853-93-020-10-001000](#) [852-90-020-10-001000](#) [853-93-012-10-001000](#) [853-93-018-10-001000](#) [851-93-003-10-002000](#) [851-93-008-10-002000](#) [850-10-010-10-001000](#) [851-93-006-10-001000](#) [851-93-007-10-001000](#) [852-10-100-10-001000](#) [852-10-020-10-001000](#) [851-93-003-10-001000](#) [853-13-100-10-001000](#) [853-93-100-10-001000](#) [853-43-050-10-001000](#) [852-40-100-10-001000](#) [852-40-050-10-001000](#) [851-43-077-10-002000](#) [851-43-025-10-001000](#) [850-40-050-10-001000](#) [850-40-025-10-001000](#) [850-10-025-10-001000](#) [852-10-016-10-001000](#) [851-43-050-10-001000](#) [850-10-003-10-001000](#) [850-40-012-10-001000](#) [851-43-008-10-002000](#) [851-43-012-10-002000](#) [853-93-068-10-001000](#) [850-10-002-10-001000](#) [850-10-004-10-001000](#) [851-43-002-10-001000](#) [852-10-006-10-001000](#) [853-43-014-10-001000](#) [853-93-014-10-001000](#) [850-40-006-10-001000](#) [851-43-008-10-001000](#) [853-93-010-10-001000](#) [851-43-004-10-001000](#) [851-43-006-10-001000](#)