

PIN RECEPTACLES

FOR .040" - .050" DIAMETER PINS (#02 CONTACT)
FOR .040" - .060" DIAMETER PINS (#03 CONTACT)

<p>0355 0355-0-15-XX-02-XX-10-0 Solder mount in .102 min. mounting hole</p>	<p>0354 0354-0-15-XX-02-XX-10-0 Pentagonal press-fit in .104 min. plated through-hole</p>	<p>3490 3490-0-15-XX-02-XX-10-0 Press-fit in .091 mounting hole</p>	<p>3808 3808-0-15-XX-02-XX-10-0 Press-fit in .090 mounting hole</p>
<p>9184 9184-0-15-XX-02-XX-40-0 Bottom entry, surface mount .092 min. plated through-hole Also available on carrier tape, See page 194.12 for Tape & Reel details</p>	<p>9222 9222-2-15-XX-02-XX-40-0 Bottom entry, surface mount .082 min. plated through-hole Also available on carrier tape, See page 194.12 for Tape & Reel details</p>	<p>4064 4064-0-18-XX-03-XX-40-0 Surface mount Also available on 16mm wide carrier tape: 2,400 parts per 13" reel See page 194.13 for Tape & Reel details</p> <p>P.C.B. Layout</p>	

SPECIFICATIONS:

Shell Material: Brass Alloy 360, 1/2 Hard
Contact Material: Beryllium Copper Alloy 172, HT
Dimensions: Inches
Tolerances On: Lengths: ±.005
 Diameters: ±.002
 Angles: ± 2°



ORDER CODE: XXXX - X - XX - XX - XX - XX - 0

BASIC PART #

SPECIFY SHELL FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 15 10 μ" GOLD OVER NICKEL (RoHS)

SPECIFY CONTACT FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 27 30 μ" GOLD OVER NICKEL (RoHS)

SELECT CONTACT:

#02 or #03 CONTACT (DATA ON PAGE 259)
 (For alternate contact choices, see group F on page 248)



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mill-Max:

[0355-0-15-80-02-80-10-0](#) [0355-0-15-80-02-27-10-0](#) [0355-0-15-15-02-27-10-0](#) [0354-0-15-15-02-27-10-0](#) [0355-0-15-01-02-27-10-0](#) [0355-0-15-01-02-01-10-0](#) [0354-0-15-01-02-27-10-0](#) [3808-0-15-15-02-14-10-0](#) [0354-0-15-01-02-01-10-0](#) [3808-0-15-15-02-27-10-0](#) [9225-0-15-00-00-00-10-0](#) [0355-0-15-00-00-00-10-0](#) [3490-0-15-00-00-00-10-0](#) [0354-0-15-00-00-00-10-0](#) [3808-0-15-01-02-14-10-0](#) [3490-0-15-01-02-14-10-0](#) [3808-0-15-80-02-14-10-0](#) [0355-0-15-80-02-14-10-0](#) [3490-0-15-80-02-14-10-0](#) [0354-0-15-80-02-14-10-0](#) [0354-0-15-01-02-14-10-0](#) [0354-0-15-15-02-14-10-0](#) [0355-0-15-15-02-14-10-0](#)