



**Fair-Rite Products Corp.**

Your Signal Solution®

# EFD Cores (8978303021)



Part Number: 8978303021

78 EFD CORE SET

**EFD (Economical Flat Design) cores have been designed to maximize volume in a low profile geometry. EFD cores allow maximum throughput power density with reasonably low mass for board level installation.**

EFD cores can be supplied with the center post gapped to a mechanical dimension or an  $A_L$  value.


[Catalog Drawing](#)

[3D Model](#)

Weight indicated is per pair or set.

Weight: 24 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	30	$\pm 0.80$	1.181	—
B	15	$\pm 0.25$	0.591	—
C	9.1	$\pm 0.30$	0.358	—
D	11.2	$\pm 0.30$	0.441	—
E	22.4	$\pm 0.75$	0.882	—
F	14.6	$\pm 0.30$	0.575	—
K	4.9	$\pm 0.20$	0.193	—



## Chart Legend

$\Sigma l/A$  : Core Constant,  $l_e$  : Effective Path Length,  $A_e$  : Effective Cross- Sectional Area,  $V_e$  : Effective Core Volume  
 $A_L$  : Inductance Factor

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
$A_L$ (nH)	$2100 \pm 25\%$
$A_e$ (cm <sup>2</sup> )	0.69
$\Sigma l/A$ (cm <sup>-1</sup> )	11.3
$l_e$ (cm)	6.93
$V_e$ (cm <sup>3</sup> )	4.26
$A_{min}$ (cm <sup>2</sup> )	0.66

$A_L$  value is measured at 1 kHz, B < 10 gauss.

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288

888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • [ferrites@fair-rite.com](mailto:ferrites@fair-rite.com) • [www.fair-rite.com](http://www.fair-rite.com)

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Fair-Rite:](#)

[8978303021](#)