



CRYSTEK
MICROWAVE
A DIVISION OF CRYSTEK CORPORATION

RG-316 MMCX RF COAX CABLE ASSEMBLIES



RG316 50 Ohm MMCX Coaxial Cables

MMCX / MMCX [Male Straight / Male Straight]

MMCX / MMCX RA [Male Straight / Male Right Angle]

MMCX RA / MMCX RA [Male Right Angle / Male Right Angle]

SMA FB / MMCX [Female Bulk Head / Male Straight]

SMA FB / MMCX RA [Female Bulkhead / Male Right Angle]

Features:

Bandwidth:	DC to 6 GHz
Strain Relief:	Adhesive shrink tubing over crimp area
Center Conductor:	[7/.0067"] SCCS (Silver Coated Copper Covered Steel)
Shielding:	SPC (Silver-Plated Copper)
Insulation:	PTFE (Polytetrafluoroethylene) dielectric
Cable Outer Diameter:	0.098" (2.49mm)
Jacket:	FEP (Fluorinated Ethylene Propylene)
Connector:	Gold-plated brass
Operating Temperature:	-40°C to +85°C
Minimum Bend Radius:	0.5"

Custom Lengths Available

(Minimum Order Quantity Required)

Actual Electrical Data:

PN: CCMX-MM-RG316-12

Freq. (MHz)	Insertion Loss
50	-0.36
500	-0.40
1000	-0.45
2000	-0.55
3000	-0.60
4000	-0.72
5000	-0.79
6000	-0.86



MMCX / MMCX [Male Straight / Male Straight]

Part Number	Description	Length
CCMX-MM-RG316-6	RG316 Shielded Cable, MMCX Male STR / Male STR	6"
CCMX-MM-RG316-12	RG316 Shielded Cable, MMCX Male STR / Male STR	12"
CCMX-MM-RG316-18	RG316 Shielded Cable, MMCX Male STR / Male STR	18"
CCMX-MM-RG316-24	RG316 Shielded Cable, MMCX Male STR / Male STR	24"



CRYSTEK
CORPORATION

12730 COMMONWEALTH DRIVE • FORT MYERS, FL 33913

PHONE: 239-561-3311 • 800-237-3061 Rev.: A

FAX: 239-561-1025 • WWW.CRYSTEK.COM Date: 03-01-14



CRYSTEK
MICROWAVE
A DIVISION OF CRYSTEK CORPORATION

RG-316 MMCX RF COAX CABLE ASSEMBLIES



MMCX / MMCX RA [Male Straight / Male Right Angle]

Part Number	Description	Length
CCMX1-MM-RG316-6	RG316 Shielded Cable, MMCX Male STR / Male RA	6"
CCMX1-MM-RG316-12	RG316 Shielded Cable, MMCX Male STR / Male RA	12"
CCMX1-MM-RG316-18	RG316 Shielded Cable, MMCX Male STR / Male RA	18"
CCMX1-MM-RG316-24	RG316 Shielded Cable, MMCX Male STR / Male RA	24"

MMCX RA / MMCX RA [Male Right Angle / Male Right Angle]

Part Number	Description	Length
CCMX2-MM-RG316-6	RG316 Shielded Cable, MMCX Male RA / Male RA	6"
CCMX2-MM-RG316-12	RG316 Shielded Cable, MMCX Male RA / Male RA	12"
CCMX2-MM-RG316-18	RG316 Shielded Cable, MMCX Male RA / Male RA	18"
CCMX2-MM-RG316-24	RG316 Shielded Cable, MMCX Male RA / Male RA	24"

SMA FB / MMCX [Female Bulk Head / Male Straight]

Part Number	Description	Length
CCSMX-FBM-RG316-6	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male STR	6"
CCSMX-FBM-RG316-12	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male STR	12"
CCSMX-FBM-RG316-18	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male STR	18"
CCSMX-FBM-RG316-24	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male STR	24"

SMA FB / MMCX [Female Bulk Head / Male Right Angle]

Part Number	Description	Length
CCSMX1-FBM-RG316-6	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male RA	6"
CCSMX1-FBM-RG316-12	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male RA	12"
CCSMX1-FBM-RG316-18	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male RA	18"
CCSMX1-FBM-RG316-24	RG316 Shielded Cable, SMA Female Bulkhead / MMCX Male RA	24"



CRYSTEK
CORPORATION

12730 COMMONWEALTH DRIVE • FORT MYERS, FL 33913

PHONE: 239-561-3311 • 800-237-3061 Rev.: A

FAX: 239-561-1025 • WWW.CRYSTEK.COM Date: 03-01-14

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Crystek:

[CCSMX-FBM-RG316-6](#) [CCSMX-FBM-RG316-12](#) [CCSMX-FBM-RG316-18](#) [CCSMX-FBM-RG316-24](#) [CCSMX1-FBM-RG316-6](#) [CCSMX1-FBM-RG316-12](#) [CCSMX1-FBM-RG316-18](#) [CCSMX1-FBM-RG316-24](#) [CCMX-MM-RG316-6](#) [CCMX-MM-RG316-12](#) [CCMX-MM-RG316-18](#) [CCMX-MM-RG316-24](#) [CCMX2-MM-RG316-6](#) [CCMX2-MM-RG316-12](#) [CCMX2-MM-RG316-18](#) [CCMX2-MM-RG316-24](#) [CCMX1--MM-RG316-6](#) [CCMX1--MM-RG316-12](#) [CCMX1--MM-RG316-18](#) [CCMX1--MM-RG316-24](#)