


# WRAPOST RECEPTACLES

FOR .015" - .025" DIAMETER PINS

## 0444

0444-X-17-XX-30-XX-02-0

Press-fit in .056 mounting hole




| Basic Part Number | # of Wraps | Length A |
|-------------------|------------|----------|
| 0444-1            | 1          | .260     |
| 0444-2            | 2          | .370     |
| 0444-3            | 3          | .505     |

## 2601 ⇨ 2603

260X-0-17-XX-30-XX-02-0

Press-fit in .057 mounting hole




| Basic Part Number | # of Wraps | Length A |
|-------------------|------------|----------|
| 2601-0            | 1          | .232     |
| 2602-0            | 2          | .350     |
| 2603-0            | 3          | .468     |

## 0445

0445-3-17-XX-30-XX-02-0


Press-fit in .056 mounting hole



## 1047

1047-3-17-XX-30-XX-02-0

Press-fit in .056 mounting hole



### SPECIFICATIONS:

**Shell Material:** Brass Alloy 360, 1/2 Hard

**Contact Material:** Beryllium Copper Alloy 172, HT

**Dimensions:** Inches

**Tolerances On:** Lengths: ±.005

Diameters: ±.002

Angles: ± 2°



**ORDER CODE:** XXXX - X - 17 - XX - 30 - XX - 02 - 0

**BASIC PART #**

**SPECIFY SHELL FINISH:**

01 200 μ" TIN/LEAD OVER NICKEL

◆ 80 200 μ" TIN OVER NICKEL (RoHS)

◆ 15 10 μ" GOLD OVER NICKEL (RoHS)

**SPECIFY CONTACT FINISH:**

02 100 μ" TIN/LEAD OVER NICKEL

◆ 84 100 μ" TIN OVER NICKEL (RoHS)

◆ 27 30 μ" GOLD OVER NICKEL (RoHS)

**SELECT CONTACT:**

#30 or #32 CONTACT (DATA ON PAGE 253)

(For alternate contact choices, see groups B and C on page 248)



Mill-Max Mfg. Corp. • 190 Pine Hollow Road, P.O. Box 300, Oyster Bay, NY 11771 • 516-922-6000 • Fax: 516-922-9253 • www.mill-max.com

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Mill-Max:

[2603-0-17-01-30-02-02-0](#) [2603-0-17-01-30-27-02-0](#) [2602-0-17-01-30-02-02-0](#) [2602-0-17-01-30-27-02-0](#) [2601-0-17-01-30-02-02-0](#) [2601-0-17-01-30-27-02-0](#) [1047-3-17-01-30-02-02-0](#) [1047-3-17-01-30-27-02-0](#) [0445-3-17-01-30-02-02-0](#) [0445-3-17-01-30-27-02-0](#) [0444-3-17-01-30-02-02-0](#) [0444-3-17-01-30-27-02-0](#) [0444-2-17-01-30-02-02-0](#) [0444-2-17-01-30-27-02-0](#) [0444-1-17-01-30-02-02-0](#) [0444-1-17-01-30-27-02-0](#) [0444-1-17-15-30-27-02-0](#) [0444-2-17-15-30-27-02-0](#) [0444-3-17-15-30-27-02-0](#) [0445-3-17-15-30-27-02-0](#) [1047-3-17-15-30-27-02-0](#) [2601-0-17-15-30-27-02-0](#) [2602-0-17-15-30-27-02-0](#) [2603-0-17-15-30-27-02-0](#) [2603-0-17-00-00-00-02-0](#) [0444-3-17-00-00-00-02-0](#) [1047-3-17-00-00-00-02-0](#) [2602-0-17-00-00-00-02-0](#) [0444-2-17-00-00-00-02-0](#) [0445-3-17-00-00-00-02-0](#) [0444-1-17-00-00-00-02-0](#) [2602-0-17-01-30-14-02-0](#) [2603-0-17-01-30-14-02-0](#) [2601-0-17-80-30-14-02-0](#) [0444-3-17-80-30-14-02-0](#) [0445-3-17-01-30-14-02-0](#) [0444-3-17-01-30-14-02-0](#) [0445-3-17-80-30-14-02-0](#) [0444-2-17-01-30-14-02-0](#) [0444-2-17-80-30-14-02-0](#) [1047-3-17-80-30-14-02-0](#) [0444-1-17-01-30-14-02-0](#) [0444-1-17-80-30-14-02-0](#) [2603-0-17-80-30-14-02-0](#) [2602-0-17-80-30-14-02-0](#) [2601-0-17-01-30-14-02-0](#) [1047-3-17-01-30-14-02-0](#) [0446-2-17-01-30-27-02-0](#) [0446-2-17-01-30-02-02-0](#) [0446-2-17-80-30-84-02-0](#) [0446-2-17-80-30-27-02-0](#) [0446-2-17-15-30-27-02-0](#)