

Catalog

.NET Micro Framework

System on Module

.NET Gadgeteer

Kit

Mainboard

Module

Accessories

Other

File System

Sale

What we Offer

Comparison

Locate a Distributor

CAN DW Module

Part #: CANDW-GM-311

Overview

Downloads (4)



Description

Gadgeteer specifications include a CAN socket type which exposes the CAN TX and CAN RX digital lines. This leaves the option of selecting a transceiver up to the module. For example, this can be a High Speed Dual Wire, Single Wire or even Low Speed Fault Tolerant.

This module offers a High Speed, up to 1mbps, dual wire transceiver. The required 120ohm termination resistors are already included on the module but can be disconnected by desoldering the SMT jumper.

- Socket: C
- Size: 47mm x 39mm
- Weight: 9g
- 3.3V Consumption : 0mA
- 5V Consumption: 18mA
- Includes one [Gadgeteer cable](#)

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[GHI Electronics:](#)

[CANDW-GM-311](#)