

Is Now Part of



## **ON Semiconductor**®

# To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (\_), the underscore (\_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (\_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at <a href="mailto:www.onsemi.com">www.onsemi.com</a>. Please email any questions regarding the system integration to <a href="mailto:Fairchild\_questions@onsemi.com">Fairchild\_questions@onsemi.com</a>.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or unavteries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or i, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor and is officers, employees, uniotificated use, even if such claim any manner.




## KA339/KA339A, KA2901 Quad Comparator

#### **Features**


- Single or Dual Supply Operation
- Wide Range of Supply Voltage KA339/KA339A, KA2901 : 2 ~ 36V (or ±1 ~ ±18V)
- Low Supply Current Drain 800µA Typ.
- Open Collector Outputs for Wired and Connectors
- Low Input Bias Current 25nA Typ.
- Low Input Offset Current ±2.3nA Typ.
- Low Input Offset Voltage ±1.4mV Typ.
- Input Common Mode Voltage Range Includes Ground.
- Low Output Saturation Voltage
- Output Compatible With TTL, DTL and MOS Logic System

## Description


The KA339/KA339A, KA2901 consist of four independent voltage comparators designed to operate from single power supply over a wide voltage range.



## **Internal Block Diagram**



## Schematic Diagram



## **Absolute Maximum Ratings**

| Parameter                                       | Symbol   | Value                | Unit |
|---|----------|----------------------|------|
| Supply Voltage                                  | Vcc      | ±18 or 36            | V    |
| Differential Input Voltage                      | VI(DIFF) | 36                   | V    |
| Input Voltage                                   | VI       | -0.3 to +36          | V    |
| Output Short Circuit to GND                     | -        | Continuous           | -    |
| Power Dissipation                               | PD       | 570                  | mW   |
| Operating Temperature<br>KA339/KA339A<br>KA2901 | TOPR     | 0 ~ +70<br>-40 ~ +85 | °C   |
| Storage Temperature                             | TSTG     | -65 ~ +150           | °C   |

## **Electrical Characteristics**

| Deremeter                     | Symbol                     | Condi  | Conditions |      | KA339A |         |      | KA339 |         |       |
|-------------------------------|----------------------------|--|------------|------|--------|---------|------|-------|---------|-------|
| Parameter                     | Parameter Symbol Condition |  | tions      | Min. | Тур.   | Max.    | Min. | Тур.  | Max.    | Unit  |
|                               | Vio                        | VO(P) = 1.4V,  | Rs = 0Ω    | -    | 1      | 2       | -    | 1.4   | 5       | mV    |
| Input Offset Voltage VIO      |                            | Note1  |            | -    | -      | 4.0     | -    | -     | 9.0     |       |
| Input Offset Current          | lio                        | IIN(+) - IIN(-), \   | VCM = 0V   | -    | 2.3    | 50      | -    | 2.3   | 50      | nA    |
| input Onset Ourrent           | 10                         |  | Note1      | -    | -      | 150     | -    | -     | 150     |       |
| Input Bias Current            | IBIAS                      | VCM = 0V   |            | -    | 57     | 250     | -    | 57    | 250     | nA    |
| input bias ourient            | IDIAS                      |  | Note1      | -    | -      | 400     | -    | -     | 400     |       |
| Input Common Mode             | VI(R)                      | VCC = 30V  |            | 0    | -      | Vcc-1.5 | 0    | -     | Vcc-1.5 | V     |
| Voltage Range                 | VI(IN)                     |  | Note1      | 0    | -      | Vcc-2   | 0    | -     | Vcc-2   | v     |
| Supply Current                | ICC                        | $V_{CC} = 5V, R_L = \infty$  |            | -    | 1.1    | 2.0     | -    | 1.1   | 2.0     | mA    |
| Voltage Gain                  | Gv                         | $V_{CC}$ = 15V, $R_L \ge 15k\Omega$<br>(for large swing)                               |            | 50   | 200    | -       | 50   | 200   | -       | V/mV  |
| Large Signal<br>Response Time | TLRES                      | $V_{I} = TTL Logic Swing$ $V_{REF} = 1.4V, V_{RL} = 5V,$ $R_{L} = 5.1 k\Omega (Note2)$ |            | -    | 300    | -       | -    | 300   | -       | ns    |
| Response Time                 | TRES                       | V <sub>RL</sub> = 5V, R <sub>L</sub> = 5.1kΩ<br>(Note2)                                |            | -    | 1.3    | -       | -    | 1.3   | -       | μs    |
| Output Sink Current           | ISINK                      | $V_{I(-)} \ge 1V, V_{I(+)} = 0V, V_{O(P)} \le 1.5V$                                    |            | 6    | 18     | -       | 6    | 18    | -       | mA    |
| Output Saturation VSA         | Veat                       | $VI(-) \ge 1V, VI(+) = 0V$   |            | -    | 140    | 400     | -    | 140   | 400     | mV    |
|                               | ISINK = 4                  | ISINK = 4mA  | Note1      | -    | -      | 700     | -    | -     | 700     | 111.V |
| Output Leakage                |                            | $V_{I(-)} = 0V$  | VO(P) = 5V | -    | 0.1    | -       | -    | 0.1   | -       | nA    |
| Current                       | l <sub>o</sub> (LKG)       | VI(+) = 1V   | VO(P) =30V | -    | -      | 1.0     | -    | -     | 1.0     | μA    |
| Differential Voltage          | VI(DIFF)                   | Note1  |            | -    | -      | 36      | -    | -     | 36      | V     |

#### Note:

1. KA339 / KA339A:  $0 \le T_A \le +70^{\circ}C$ 

KA2901: -40  $\leq$  TA  $\leq$  +85°C

2. These parameters, although guaranteed, are not 100% tested in production.

### Electrical Characteristics (Continued)

(V<sub>CC</sub> = 5V,  $T_A$  = 25°C, unless otherwise specified)

| Deveryoter                    | Querra ha a l     | Conditions  |             |      | 11          |         |        |  |
|-------------------------------|-------------------|---|-------------|------|-------------|---------|--------|--|
| Parameter                     | Symbol Conditions |   | aitions     | Min. | Min. Typ. M |         | – Unit |  |
|                               | Vio               | VO(P) = 1.4V,   | Rs = 0Ω     | -    | 2           | 7       | mV     |  |
| Input Offset Voltage VIO      |                   | Note1   |             | -    | 9           | 15      | ΠIV    |  |
| Input Offset Current          | lio               |   |             | 2.3  | 50          | nA      |        |  |
| input Onset Current           |                   |   | Note1       | -    | 50          | 200     |        |  |
| Input Bias Current            |                   |   |             | -    | 57          | 250     | nA     |  |
| Input Bias Current IBIAS      |                   |   | Note1       | -    | 200         | 500     |        |  |
| Input Common                  |                   | KA2901, VCC   | =30V        | 0    | -           | Vcc-1.5 |        |  |
| Mode<br>Voltage Range         | VI(R)             |   | Note1       | 0    | -           | Vcc-2   | V      |  |
|                               | Icc               | RL =∞, VCC=5V   |             | -    | 1.1         | 2.0     |        |  |
| Supply Current IC             |                   | RL =∞, VCC =30V   |             | -    | 1.6         | 2.5     | mA     |  |
| Voltage Gain                  | Gv                | V <sub>CC</sub> =15V, R <sub>L</sub> ≥15kΩ<br>(for large swing)           |             | 25   | 100         | -       | V/mV   |  |
| Large Signal<br>Response Time | TLRES             | VI =TTL Logic Swing<br>VREF =1.4V, VRL = 5V,<br>RL =5.1k $\Omega$ (Note2) |             | -    | 300         | -       | ns     |  |
| Response Time                 | TRES              | V <sub>RL</sub> = 5V, R <sub>L</sub> =5.1kΩ (Note2)                       |             | -    | 1.3         | -       | μS     |  |
| Output Sink Current           | ISINK             | $V_{I(-)} \ge 1V, V_{I(+)} = 0V, V_{O(P)} \le 1.5V$                       |             | 6    | 18          | -       | mA     |  |
| Output Saturation             |                   | VI(-) ≥ 1V, VI(+) =0V   |             | -    | 140         | 400     |        |  |
| Voltage                       | VSAT              | ISINK = 4mA   | Note1       | -    | -           | 700     | mV     |  |
| Output Leakage                |                   | $V_{I(-)} = 0V$ $V_{I(+)} = 1V$   | VO(P) = 5V  | -    | 0.1         | -       | nA     |  |
| Current                       | U(LKG)            |   | VO(P) = 30V | -    | -           | 1.0     | μA     |  |
| Differential Voltage          | VI(DIFF)          | - Note1   |             | -    | -           | 36      | V      |  |

#### Note:

1. KA339 / KA339A:  $0 \leq T_A \leq +70^\circ C$ 

KA2901: -40  $\leq$  TA  $\leq$  +85°C

2. These parameters, although guaranteed, are not 100% tested in production.

## **Typical Performance Characteristics**




Figure 1. Supply Current vs Supply Voltage




Figure 3. Output Saturation Voltage vs Sink Current




Figure 5. Response Time for Various Input Overdrive-Positive Transition




Figure 2. Input Current vs Supply Voltage





Figure 4. Response Time for Various Input Overdrive-Negative Transition

### **Mechanical Dimensions**

#### Package

#### **Dimensions in millimeters**




**14-DIP** 

#### Mechanical Dimensions (Continued)

#### Package






**14-SOP** 

NOTES: UNLESS OTHERWISE SPECIFIED

- A. THIS PACKAGE REFERENCE TO JEDEC MS-012
- VARIATION AB.
- B. ALL DIMENSIONS ARE IN MILLIMETERS.
- C. DIMENSIONS ARE EXCLUSIVE OF BURRS, MOLD FLASH AND TIE BAR EXTRUSIONS.
- D. DIMENSIONS AND TOLERANCES AS PER ASME
- DIMENSIONS AND TOLERAINCES AS FER ASME Y14.5-1994.
  OUT OF JEDEC STANDARD VALUE.
  F. LAND PATTERN STANDARD: SOIC127P600X145-14M.
  G. FILE NAME: MKT-M14C REV2



### **Ordering Information**

| Product Number | Package | Operating Temperature |  |  |  |
|----------------|---------|-----------------------|--|--|--|
| KA339          | 14-DIP  |                       |  |  |  |
| KA339A         |         | 0 ~ +70°C             |  |  |  |
| KA339D         | 14-SOP  | 0~+70 8               |  |  |  |
| KA339AD        | 14-30F  |                       |  |  |  |
| KA2901D        | 14-SOP  | -40 ~ +85°C           |  |  |  |

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- 2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor has against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death ass

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

ON Semiconductor: KA339ADTE KA339A